

Europäisches Patentamt
European Patent Office
Office européen des brevets



(11) **EP 0 931 388 B1**

(12)

EUROPEAN PATENT SPECIFICATION

(45) Date of publication and mention
of the grant of the patent:
05.11.2003 Bulletin 2003/45

(51) Int Cl.7: **H04B 7/02, H04B 7/10,
H01Q 3/40, H01Q 3/26,
H04B 7/04**

(21) Application number: **97940660.0**

(86) International application number:
PCT/US97/15160

(22) Date of filing: **27.08.1997**

(87) International publication number:
WO 98/009385 (05.03.1998 Gazette 1998/09)

(54) SPATIO-TEMPORAL PROCESSING FOR COMMUNICATION

RAUMZEITLICHE SIGNALVERARBEITUNG FÜR ÜBERTRAGUNGSSYSTEME

TRAITEMENT SPATIO-TEMPOREL POUR TELECOMMUNICATIONS

(84) Designated Contracting States:
DE FI FR GB NL SE

(30) Priority: **29.08.1996 US 25227 P**
29.08.1996 US 25228 P

(43) Date of publication of application:
28.07.1999 Bulletin 1999/30

(73) Proprietor: **Cisco Technology, Inc.**
San Jose, CA 95134-1706 (US)

(72) Inventors:
• **RALEIGH, Gregory, G.**
El Granada, CA 94018 (US)

• **JONES, Vincent, K.**
Redwood Shores, CA 94065 (US)
• **POLLOCK, Michael, A.**
Cupertino, CA 95014 (US)

(74) Representative: **Kazi, Ilya et al**
Mathys & Squire,
100 Gray's Inn Road
London WC1X 8AL (GB)

(56) References cited:
EP-A- 0 253 465 WO-A-95/22873
WO-A-96/30964 US-A- 5 510 799

Note: Within nine months from the publication of the mention of the grant of the European patent, any person may give notice to the European Patent Office of opposition to the European patent granted. Notice of opposition shall be filed in a written reasoned statement. It shall not be deemed to have been filed until the opposition fee has been paid. (Art. 99(1) European Patent Convention).

Description

BACKGROUND OF THE INVENTION

5 [0001] The present invention relates to digital communication and more particularly to a space-time communication system.

[0002] The ability to communicate through wireless media is made difficult by the inherent characteristics of how transmitted signals propagate through the environment. A communication signal transmitted through a transmitter antenna element travels along multiple paths to the receiving antenna element. Depending on many factors including
10 the signal frequency and the terrain, the paths along which the signal travels will exhibit different attenuation and propagation delays. This results in a communication channel which exhibits fading and delay spread.

[0003] It is well known that adaptive spatial processing using multiple antenna arrays increases the communications quality of wireless systems. Adaptive array processing is known to improve bit error rate, data rate, or spectral efficiency in a wireless communication system. The prior art provides for methods involving some form of space-time signal
15 processing at either the input to the channel, the output to the channel, or both. The space-time processing step is typically accomplished using an equalization structure wherein the time domain equalizer tap settings for a multitude of antennas are simultaneously optimized. This so-called "space-time equalizaion" leads to high signal processing complexity if the delay spread of the equivalent digital channel is substantial.

[0004] There is prior art teaching the use of conventional antenna beams or polarizations to create two or more spatially isolated communication channels between a transmitter and a receiver, but only under certain favorable conditions. The radiation pattern cross talk between different physical transmit and receive antenna pairs must provide sufficient spatial isolation to create two or more substantially independent communication channels. This can lead to stringent manufacturing and performance requirements on the physical antenna arrays as well as the receiver and transmitter electronics. In addition, when large objects in the wireless propagation channel cause multipath reflections,
20 the spatial isolation provided by the prior art between any two spatial subchannels can be severely degraded, thus reducing communication quality.

[0005] EP-A-0253465 discloses a beam forming antenna system in which a plurality of beam forming networks are connected to a plurality of antenna array elements, each beam forming network having a plurality of output terminals corresponding to the plurality of antenna array elements. The system is designed to produce multiple beams from a single array of antenna elements for use in radar applications.
30

[0006] US-A-5510799 discloses a digital signal processing method for beam forming using a multi element phased array antenna for steering an agile beam to be steered between three adjacent orthogonal beams.

[0007] WO-A-95/22873 discloses a transceiver for a cellular communication system in which an antenna array communicates with a plurality of mobile stations. A spatial filter has as many outputs as there are array elements and as many inputs as there are spatial channels.
35

[0008] Embodiments of the invention aim to provide a system for more effectively taking advantage of multiple transmitter antennas and/or multiple receiver antennas to ameliorate the deleterious effects of the inherent characteristics of wireless media.

[0009] A first transmitting method aspect provides a method of transmitting data as set out in Claim 1. Preferred features of the first aspect are set out in Claims 2 to 25.
40

[0010] A corresponding first transmitting apparatus aspect is set out in Claim 26, with preferred features set out in Claims 27 to 51.

[0011] A first receiving method aspect which complements the first transmitting method aspect is set out in Claim 52, with preferred features set out in Claims 53 to 77 and a corresponding first receiving apparatus aspect is set out in Claim 78, with preferred features set out in Claims 79 to 102.
45

[0012] A related second transmitting apparatus aspect, using encoding/decoding, is set out in Claim 103, with a complementary receiving apparatus aspect set out in Claim 109 and preferred features set out in Claims 104-108 and 110-114.

[0013] Embodiments of the present invention may provide a space-time signal processing system with advantageously reduced complexity. The system may take advantage of multiple transmitter antenna elements and/or multiple receiver antenna elements, or multiple polarizations of a single transmitter antenna element and/or single receiver antenna element. The system is not restricted to wireless contexts and may exploit any channel having multiple inputs or multiple outputs and certain other characteristics. In certain embodiments, multi-path effects in a transmission medium cause a multiplicative increase in capacity.
50

[0014] One wireless embodiment operates with an efficient combination of a substantially orthogonalizing procedure (SOP) in conjunction with a plurality of transmitter antenna elements with one receiver antenna element, or a plurality of receiver antenna elements with one transmit antenna element, or a plurality of both transmitter and receiver antenna elements. The SOP decomposes the time domain space-time communication channel that may have inter symbol
55

interference (ISI) into a set of parallel, space-frequency, SOP bins wherein the ISI is substantially reduced and the signal received at a receiver in one bin of the SOP is substantially independent of the signal received in any other bin of the SOP. A major benefit achieved thereby is that the decomposition of the ISI-rich space time channel into substantially independent SOP bins makes it computationally efficient to implement various advantageous spatial processing techniques embodied herein. The efficiency benefit is due to the fact that the total signal processing complexity required to optimize performance in all of the SOP bins is often significantly lower than the processing complexity required to jointly optimize multiple time domain equalizers.

[0015] Another benefit is that in many types of wireless channels where the rank of the matrix channel that exist between the transmitter and the receiver within each SOP bin is greater than one, the combination of an SOP with spatial processing can be used to efficiently provide multiple data communication subchannels within each SOP bin. This has the desirable effect of essentially multiplying the spectral data efficiency of the wireless system. A further feature is the use of spatial processing techniques within each transmitter SOP bin to reduce radiated interference to unintentional receivers. A still further feature is the ability to perform spatial processing within each receiver SOP bin to reduce the deleterious effects of interference from unintentional transmitters.

[0016] One advantageous specific embodiment for the SOP is to transmit with IFFT basis functions and receive with FFT basis functions. This particular SOP is commonly referred to as discrete orthogonal frequency division multiplexing (OFDM), and each SOP bin is thus associated with a frequency bin. This embodiment enhances OFDM with the addition of efficient spatial processing techniques.

[0017] In preferred embodiments of the present invention, space-frequency processing may adaptively create substantially independent spatial subchannels within each SOP bin even in the presence of significant cross talk interference between two or more physical transmit and receive antenna pairs. A further advantage is that the space-frequency processing can advantageously adapt to cross talk interference between the physical antenna pairs even if this cross-talk is frequency dependent, or time varying, or both. Thus, the present invention may provide two or more substantially independent communication channels even in the presence of severe multipath and relatively poor physical antenna radiation pattern performance.

[0018] An embodiment of the invention will now be described, with reference to the attached drawings in which:-

BRIEF DESCRIPTION OF THE DRAWINGS

[0019]

Fig. 1 depicts a transmitter system according to one embodiment of the present invention.

Fig. 2 depicts a particular substantial orthogonalizing procedure (SOP) useful in one embodiment of the present invention.

Fig. 3 depicts a receiver system according to one embodiment of the present invention.

Fig. 4 depicts a first communication scenario where multipath is found.

Fig. 5 depicts a second communication scenario where multipath is found.

Fig. 6 depicts a third communication scenario where multipath is found.

Fig. 7 depicts a multiple-input, multiple-output (MIMO) channel with interference.

Fig. 8 depicts the use of an SOP in a single-input single-output (SISO) channel.

Fig. 9 depicts the use of an SOP in a MIMO channel according to one embodiment of the present invention.

Fig. 10 depicts the operation of an SOP in the context of one embodiment of the present invention.

Fig. 11 depicts the application of spatial processing to a particular SOP bin at the transmitter end according to one embodiment of the present invention.

Fig. 12 depicts the application of spatial processing to a particular SOP bin at the receiver end according to one embodiment of the present invention.

Fig. 13 depicts the application of spatial processing to N SOP bins at the transmitter end according to one embodiment of the present invention.

Fig. 14 depicts the application of spatial processing to N SOP bins at the receiver end according to one embodiment of the present invention.

Fig. 15 depicts the use of a single spatial direction at the transmitter end for each bin of an SOP according to one embodiment of the present invention.

Fig. 16 depicts the use of a single spatial direction at the receiver end for each bin of an SOP according to one embodiment of the present invention.

Fig. 17 depicts the use of one or more common spatial weighting vectors for all SOP bins at the transmitter end according to one embodiment of the present invention.

Fig. 18 depicts the use of one or more common spatial weighting vectors for all SOP bins at the receiver end according to one embodiment of the present invention.

Fig. 19 depicts the use of an encoder for each SOP bin according to one embodiment of the present invention.
 Fig. 20 depicts the use of an encoder for each spatial direction according to one embodiment of the present invention.

Fig. 21 depicts the use of an encoder for each space/frequency subchannel according to one embodiment of the present invention.

Fig. 22 depicts distribution of encoder output over all space/frequency subchannels according to one embodiment of the present invention.

Fig. 23 depicts a detailed diagram of an encoder/interleaver system according to one embodiment of the present invention.

Fig. 24 depicts a transmitter system wherein multiple space/frequency subchannels are employed without spatial orthogonalization according to one embodiment of the present invention.

Fig. 25 depicts a receiver system wherein multiple space/frequency subchannels are employed without spatial orthogonalization according to one embodiment of the present invention.

Fig. 26 depicts an exemplary technique for bit loading with a trellis coder that uses a one-dimensional QAM symbol constellation.

DESCRIPTION OF SPECIFIC EMBODIMENTS

Definitions

[0020] A "channel" refers to the input symbol to output symbol relationship for a communication system. A "vector channel" refers to a channel with a single input and multiple outputs (SIMO), or multiple inputs and a single output (MISO). Each h_j entry in the vector channel h describes one of the complex path gains present in the channel. A "matrix channel" refers to a channel with multiple inputs and multiple outputs (MIMO). Each entry H_{ij} in the matrix H describes the complex path gain from input j to output i . A "space time channel" refers to the input to output relationship of a MIMO matrix channel, or a SIMO or MISO vector channel, that occurs when multipath signal propagation is present so that the channel contains delay elements that produce inter-symbol interference (ISI) as explained below.

[0021] A "spatial direction" is a one dimensional subspace within a matrix or vector communication channel. Spatial directions need not be orthogonal. A spatial direction is typically characterized by a complex input vector and a complex output vector used to weight transmitted or received signals as explained herein.

[0022] A "sub-channel" is a combination of a bin in a substantially orthogonalizing procedure (SOP) as explained below and a spatial direction within that bin. A group of spatial subchannels within an SOP bin may or may not be orthogonal

[0023] An "orthogonal dimension" is one member in a set of substantially orthogonal spatial directions.

[0024] A channel "subspace" is a characterization of the complex m -space direction occupied by one or more m -dimensional vectors. The subspace characterization can be based on the instantaneous or average behavior of the vectors. A subspace is often characterized by a vector-subspace of a covariance matrix. The covariance matrix is typically a time or frequency averaged outer product of a matrix or vector quantity. The covariance matrix characterizes a collection of average channel directions and the associated average strength for each direction.

[0025] A "two norm" metric for a vector is the sum of the squared absolute values for the elements of the vector.

[0026] A "Euclidean metric" is a two norm metric.

[0027] "Intersymbol interference" (ISI) refers to the self interference that occurs between the delayed and scaled versions of one time domain symbol and subsequent symbols received at the output of a delay spread communication channel. The channel delay spread is caused by the difference in propagation delay between the various multipath components combined with the time domain response of the RF and digital filter elements.

[0028] A "substantially orthogonalizing procedure" (SOP) is a procedure that plays a part in transforming a time domain sequence into a parallel set of substantially orthogonal bins, wherein the signals in one bin do not substantially interfere with the signals from other bins. Typically, the transformation from a time domain sequence to a set of substantially orthogonal bins requires a transmitter SOP with a set of input bins, and a receiver SOP with a set of output bins.

[0029] "Convolutional bit mapped QAM" (CBM-QAM) is the coding system that results when the output of a convolutional encoder are grouped and mapped to QAM constellation points.

[0030] Fading "structure" occurs when the fading behavior of one or more entries in a channel matrix within an SOP bin is correlated across time, or frequency, or both. This structure can be exploited using advantageously designed estimation filters to improve channel estimation accuracy given multiple frequency samples of the channel matrix entries, or multiple time samples, or both.

[0031] A "maximum likelihood sequence detector" is a sequence estimator that computes the most likely transmitted code sequence, from a set of possible sequences, by minimizing a maximum likelihood cost function.

[0032] An "antenna element" is a physical radiator used to transmit or receive radio frequency signals. An antenna

element does not involve any electronics processing components. A single radiator with two polarization feeds is viewed as two antenna elements.

[0033] An "antenna array" is a collection of antenna elements.

[0034] A "burst" is a group of transmitted or received communication symbols.

Background Material

[0035] The disclosure herein assumes a background in digital communication and linear algebra. The following references are incorporated herein by reference.

[0036] Wozencraft & Jacobs, Principles of Communication Engineering (1965).

[0037] Haykin, Adaptive Filter Theory, 2nd Ed. (1991).

[0038] Strang, Linear Algebra, 3rd Ed. (1988).

[0039] Jakes, Microwave Mobile Communication (1974).

[0040] Proakis, Digital Communications (1995).

Transmitter Overview

[0041] Fig. 1 depicts a transmitter system in accordance with one embodiment of the present invention. Typically an information signal input 2 includes a digital bit sequence, although other forms of digital data or analog data are possible. In the case of digital data, the input data sequence is first fed into an Encoder and Interleaving apparatus 10 where the data is encoded into a symbol stream. The symbol stream is typically a sequence of complex digitized values that represent members of a finite set. Each symbol can be a one dimensional value, or a multidimensional value. An exemplary one dimensional symbol set is a PAM constellation. Note that in this discussion, it is understood that a symbol with in-phase and quadrature components, is considered to be a complex one dimensional symbol, so that the QAM constellation is also viewed as a set of one dimensional symbols. An example multidimensional symbol set is a sequential grouping of QAM constellation members.

[0042] The purpose of the encoding process is to improve the bit error rate of the transmitted signal by introducing some form of information redundancy into the transmitted data stream. Useful encoding techniques can involve combinations of a number of well known techniques such as convolutional encoding with bit mapping to symbols, trellis encoding, block coding such as cyclic redundancy check or Reed Solomon coding with bit mapping or Automatic Repeat Queuing. An interleaver is often advantageous for distributing the transmitted information among the various subchannels available for transmission. This interleaving distributes the effects of channel fading and interference so that long sequences of symbols with poor quality are not grouped closely together in the SOP bin sequence that is fed into the receiver decoder. In many applications, it is advantageous to perform a power and bit-loading optimization wherein the number of bits that are mapped to a given encoder symbol, and the signal power assigned to that symbol, are determined based upon the measured communication quality of the space-frequency information subchannel that carries the symbol stream.

[0043] After the digital data is encoded into a sequence of symbols, a Training Symbol Injection block 20 may be used to place a set of known training symbol values in the transmitter symbol stream. The purpose of the training symbols is to provide a known input within a portion of the transmitted symbol stream so that a receiver may estimate the communication channel parameters. The channel estimate is used to aid in demodulation and decoding of the data sequence. The training symbols may be injected periodically in time, periodically in frequency, or both. It will be obvious to one skilled in the art that blind adaptive spatial processing techniques can be utilized within each SOP bin at the receiver as an alternative to training with known symbols. In such blind detection implementations, Training Symbol Injection block 20 is unnecessary.

[0044] The data plus training symbol stream is then fed into a Transmitter Space-Frequency Pre-Processor (TSFP) block 30. The TSFP block 30 performs two sets of advantageous processing steps on the symbol stream before transmission. One processing step accomplished within the TSFP is the transmitter portion of a substantially orthogonalizing procedure (SOP). When the transmitter portion of the SOP is combined with the receiver portion of the SOP, a set of parallel bins are created in such a manner that information transmitted within one bin does not substantially interfere with information transmitted from another bin after the receive portion of the SOP is completed. One preferred SOP pair is the inverse fast Fourier transform (IFFT) at the transmitter combined with the FFT at the receiver. Another advantageous SOP pair embodiment is a bank of multiple filter and frequency converter pairs (multi-band SOP) with one filter bank located at the transmitter and one filter bank located at the receiver as depicted in Fig. 2. Several other example SOPs including the Hilbert transform pair and generalized wavelet transform pairs will be obvious to one skilled in the art. The other processing step accomplished in the TSFP is spatial processing. The spatial processing step typically multiplies one or more symbols that are destined for transmission in a given SOP bin with one or more spatial vector weights. For convenience in the following discussion, the collection of spatial processing weights applied

to the signals transmitted or received in a given SOP bin are sometimes referred to as a matrix. The spatial vector weights are optimized to obtain various desirable performance enhancements.

[0045] Fig. 2 depicts a digital baseband filter bank at the receiver and a filter bank located at the transmitter. Each filter of the transmitter filter bank includes a mixer (frequency converter) 60, a bandpass filter 70 and an interpolator 80. Each filter of the receiver filter bank includes a bandpass filter 90, a mixer 60, and a decimator 100.

[0046] One transmitter embodiment optimizes the transmitter spatial vector weights so that the multiple subchannels in a given SOP bin can be converted at the receiver into substantially independent received spatial subchannels wherein symbols from one subchannel do not substantially interfere with symbols from another subchannel. Another embodiment optimizes the transmitter spatial vector weight to improve the received power of one or more spatial subchannels within each SOP bin, or to improve the average power of several spatial subchannels within several SOP bins. A further embodiment optimizes the transmitter spatial vector weights within each SOP bin to simultaneously increase the power delivered to the desired receiver within one or more spatial subchannels while reducing interference radiated to unintended receivers. A yet further embodiment spatially processes one or more symbols within each SOP bin by multiplying each symbol with a transmitter weight vector that is fixed for all SOP bins, with the weight vectors optimized to increase the time or frequency average power delivered to one or more desired receiver spatial subchannels, and possibly reduce the time or frequency averaged interference radiated to unintended receivers. This last embodiment is particularly useful in FDD systems where multipath fading makes it impossible to estimate the forward channel from reverse channel data, but where the average forward channel subspaces are substantially similar to the average reverse channel subspaces. Another embodiment teaches simply routing each symbol from the encoder to one antenna element in each SOP bin without any weighting. Other useful embodiments are discussed herein, and many others useful combinations of spatial processing with an SOP will become obvious to one skilled in the art. It is understood that one or more digital filters are typically used in TSFP 30 to shape the transmitted RF signal spectrum.

[0047] Once the encoder symbol sequence is processed by TSFP 30, the processed symbol sequence includes a parallel set of digital time domain signal sequences. Each of these time domain signal sequences is fed into one input of a Modulation and RF System block 40. Modulation and RF System block 40 includes a set of independent RF upconverter chains that frequency convert the digital baseband signal sequence up to the RF carrier frequency. This is accomplished using apparatus that includes digital to analog converters, RF mixer apparatus, and frequency synthesizer apparatus. The details of these elements of the invention are well known and will not be discussed here.

[0048] The final step in the transmission process is to radiate the transmitted signal using a Transmit Antenna Array 50. The antenna arrays can be constructed from one or more co-polarized radiating elements or there may be multiple polarizations. If there is multipath signal propagation present in the radio link, or if there are multiple polarizations in the antenna arrays, or if at least one of the antenna elements on one side of the link are in a disparate location from the other elements on the same side of the link, then the invention has the advantageous ability to create more than one subchannel within each SOP bin. It is understood that one physical antenna reflector with a feed that has two polarizations is considered as two antenna elements in all that follows. There are no restrictions on the antenna array geometry or the geometry of each radiating element. A transmitter system invention may adapt to provide optimized performance for any arbitrary antenna array.

Receiver Overview

[0049] Fig. 3 depicts a receiver system according to one embodiment of the present invention. The RF signals from each of the elements of an Antenna Array 110 are downconverted to digital baseband using a Demodulation and RF System 120. Demodulation and RF System 120 includes the RF signal processing apparatus to downconvert the RF carrier signal to a baseband IF where it is then digitized. After the digitizer, a timing and frequency synchronization apparatus is used to recover the timing of the transmitted digital signal sequence. Several known techniques may be used for the purpose of synchronization and these techniques will not be discussed herein.

[0050] In certain embodiments of the invention, after Demodulation and RF System 120, the digital baseband signal is then fed into a Channel ID block 130 and a Receiver Space-Frequency Processor (RSFP) block 140. Within Channel ID block 130, the characteristics of the digital communication channel are estimated. The estimated channel values consist of entries in a matrix for each SOP bin. The matrix contains complex values representing the magnitude of the spatial channel within the SOP bin from one transmit antenna element to one receive antenna element. The matrix channel estimate for each SOP bin is provided to RSFP block 140 and Decoder and Deinterleaving block 150.

[0051] Some embodiments of the invention involve improving channel estimation performance by exploiting the structured nature of the frequency domain fading that exists in the matrix channels across SOP bins, exploiting the structure in time domain fading of the matrix channels, or exploiting both the frequency and time domain fading structure that is present. By exploiting the frequency domain fading correlation, the entire set of matrix channels within the SOP bins may be estimated even when training information is transmitted in a subset of the SOP bins. This allows for simultaneous transmission of training and data thus reducing overhead. By exploiting the time domain correlation of the chan-

nel fading within each SOP bin, channel estimation accuracy is increased for a given time epoch between training events. This reduces the required frequency of training symbol transmission and thus further reduces training overhead. It is understood that it is also possible to separately exploit time domain and frequency domain correlation, with the most beneficial results occurring if both correlation dimensions are used advantageously. It is to be understood that Channel ID block 130 is shown as a separate function even though it may share some elements with RSFP block 140 or Decoder and Deinterleaver block 150.

[0052] RSFP block 140 performs the receiver signal processing that is the dual of the two sets of operations performed in TSFP 30. One of the steps performed in RSFP 140 is the receiver half of the SOP. As discussed above, the receiver half of the SOP completes the transformation between the time domain channel with ISI to the substantially orthogonal set of bins. The second set of signal processing operations that can be performed in the RSFP is spatial processing. In one class of embodiments, the receiver spatial processing step combines the output of the SOP bins using one or more vector weighted inner product steps to form one or more one-dimensional received spatial subchannels within each SOP bin. The receiver weight vectors are chosen to optimize an advantageous performance measure. In one embodiment, wherein both the transmitter and receiver have knowledge of the channel state information within each SOP bin, the transmitter spatial weight vectors and the receiver spatial weight vectors are both chosen to optimize performance for a set of multiple substantially independent subchannels within each SOP bin. As discussed above, this significantly increases the spectral efficiency of the system. In another embodiment wherein the transmitter does not have channel state information, the receiver performs the spatial processing required to create multiple substantially independent subchannels within each SOP bin. In a further embodiment wherein the transmitter may or may not have channel state information, the receiver reduces the effects of interference radiated from unintentional transmitters as well as performing the spatial processing required to create multiple substantially independent subchannels within each SOP bin. A yet further embodiment optimizes the receiver spatial vector weights within each SOP bin to simultaneously increase the received power and reduce the detrimental effects of interference received from unintentional transmitters. An additional embodiment involves forming one or more vector weights, that are fixed for all SOP bins, where the vector weights are optimized to simultaneously increase the time or frequency averaged received power for one or more spatial subchannels, while possibly also reducing the time or frequency averaged interference power received from unintended transmitters.

[0053] As discussed herein, certain embodiments involve simply passing the vector samples received in each SOP bin to Decoder and Deinterleaving block 150 without performing any spatial processing. It will be obvious to one skilled in the art that other combinations of transmitter spatial weight vector optimization techniques and receiver spatial weight vector optimization techniques can be constructed around the principle concept of spatial processing in combination with an SOP. Other embodiments are discussed herein. One experienced in the art will be able to recognize additional embodiments that involve advantageous combination of an SOP with spatial processing at the receiver or the transmitter. It is understood that one or more digital filters are typically used in RSFP block 1400 to shape the received RF signal spectrum.

[0054] The outputs of RSFP block 140 are fed into Decoder and Deinterleaving (DD) block 150. There are two broad exemplary classes of operation for the DD block 150. In the first exemplary broad class of embodiments, DD block 150 decodes a symbol sequence which was encoded and transmitted through a multitude of SOP bins with one or more substantially independent subchannels. The decoder includes the appropriate receiver counterparts for the combination of encoders selected for the transmitter. A preferred embodiment includes a deinterleaver, a trellis decoder or convolutional bit mapping decoder employing a scalar weighted Euclidean maximum likelihood sequence detector, followed by a Reed Solomon decoder, followed by an ARQ system to correct Reed Solomon codeword errors. In the second exemplary broad class of embodiments, DD block 150 decodes a sequence of multidimensional symbols, or groups of adjacent one dimensional symbols, with each multidimensional symbol or group of one dimensional symbols being received in an SOP bin. Typically, the symbol sequences are transmitted without weighting or with weighting that optimizes some measure of average signal quality.

[0055] In an alternative embodiment, trellis encoded symbols are grouped and interleaved in a manner such that the symbols transmitted from the antenna elements within a given SOP bin form a vector that is drawn from either a multidimensional QAM encoder output symbol, or a sequence of one dimensional QAM encoder output symbols that have adjacent locations in the pre-interleaved encoder output sequence. In this way, a maximum likelihood vector decoder may be constructed given an estimate of the channel matrix that is present within each SOP bin. The maximum likelihood decoder computes the weighted vector Euclidean metric given the deinterleaved received vector from each SOP bin, the deinterleaved matrix channel estimates from each SOP bin, and the transmitted vector symbol trellis state table.

[0056] In another alternative embodiment, either of the aforementioned encoder embodiments will have preferable performance if the encoder polynomial and symbol constellation set are optimized to improve the bit error rate performance given the characteristics of the matrix channel fading that occurs in each SOP bin. One particular metric that is well suited for a code polynomial optimization search is the product of the two norms of the vector difference between

the correct transmitter symbol vector and the error symbol vector.

[0057] The output of DD block 150 is the estimated bit stream at the receive end of the radio link.

[0058] It is to be understood that all transmitter embodiments of the present invention may be adapted for use with a receiver accessing the channel through a single channel output such as a single receiver antenna element. Furthermore, all receiver embodiments of the present invention may be adapted for use with a transmitter accessing the channel through a single channel input such as a single transmitter antenna element. It is understood that the channel is then a vector channel. Such multiple-input single-output (MISO) and single-input multiple output (SIMO) systems are within the scope of the present invention.

Space-Frequency Communication in a Multipath Channel

[0059] Before developing the signal processing of the present invention, a physical description and mathematical description of wireless channels are provided. Many wireless communication channels are characterized by multi-path, where each path has associated fading and propagation delay. Multipath may be created by reflections in the physical radio path, multiple antenna polarizations, antenna elements located in disparate locations, or a combination of any of these. One scenario in which multipath is created is illustrated in Fig 4. A Base 152 transmits information to and receives information from a remote unit 170A or 170B. Base 152 possesses one or more antenna elements referred to as an array 55. Similarly, the Remote Units possess their own arrays 55. A transmitted signal propagates along multiple paths 155A-C created by reflection and scattering from physical objects in the terrain 160A-D.

[0060] Multipath signal propagation such as that depicted in Figs. 4-6 can give rise to spatially selective fading, delay spread, frequency fading, and time fading. Spatial fading occurs as the various wavefronts arriving at the receiver from different propagation paths combine with constructive and destructive interference at different points in space. An antenna array located within this spatially selective field will sample the field at various locations so that the signal strength at each array element is different. Delay spread occurs due to the differing propagation path lengths. The channel delay spread gives rise to a frequency selective digital communication channel at each antenna element. This frequency response is different for each antenna element by virtue of the frequency dependent spatial fading. Finally, if either the transmitter, or the receiver, or objects in the terrain are moving, the frequency selective spatial fading will vary as a function of time. The present invention is unique in that it is capable of efficiently and economically adapting to the time varying space-frequency channel response to make advantageous use of the inherent properties of such channels.

[0061] For several decades, the primary focus of the prior art has been to somehow mitigate the effects of the multipath channel. This conventional approach is ill-advised since multipath channels give rise to a multiplicative capacity effect by virtue of the fact that the multipath induces a rank greater than one in the matrix channel present in each SOP bin. This provides opportunity to form multiple parallel subchannels for communication within each SOP bin. Thus, one should utilize multipath to improve communication performance rather than attempt to mitigate its effects. A substantial advantage provided by the present invention is the ability to efficiently and economically exploit the inherent capacity advantages of multipath channels using a combination of an SOP and spatial processing or spatial coding. No other structures are known to efficiently exploit this fundamental advantage in the presence of substantially frequency selective multipath channels.

[0062] Fig. 5 illustrates another wireless channel scenario in which multipath is present. A Base 152 with an antenna array 55 transmits information to and receives information from a Remote 170C with an antenna array 55. In this case, both Base and Remote antenna arrays 55 both have elements with differing polarizations. Thus multipath signal propagation exists even if there are no significant reflections in the physical environment. The direct line of sight paths 155B, 155E each corresponding to one of the polarizations in the array elements, are sufficient to create a matrix channel with a rank greater than one within each SOP bin, even if the other reflected radio paths 155A, 155C, 155D, and 155F are insignificant or nonexistent.

[0063] It is known that such line of sight polarization (reflection free) channels can be decomposed into two parallel communication channels by using high performance dual polarization antennas, one at each end of the radio link, in combination with high performance receiver and transmitter electronics apparatus. In this prior art, the quality of the parallel communication channels is limited by the degree to which the two polarization channels remain independent. In general, maintaining the manufacturing tolerances and installation alignment precision in the antennas and electronics required to achieve substantially orthogonal spatial subchannels at the output of the physical receive antenna is relatively expensive. Slight manufacturing errors and component variations can lead to a significant cross-talk interference between the multiple polarizations present in the radio channel. In contrast, an advantageous feature of the invention is that the different polarizations present in the wireless channel may have an arbitrary degree of cross-talk interference, and the cross-talk interference may be frequency dependent without loss of performance. In such cases, the invention provides an economical and efficient method for fully exploiting the multi-dimensional nature of the multiple polarization channel. It is understood that the invention can provide further capacity advantage if the multiple polari-

zation channel also has reflected signal paths. This additional multipath results in an additional increase in the channel matrix rank in each SOP bin that can be further exploited to improve the capacity of the channel.

[0064] Fig. 6 depicts another wireless communication scenario in which multipath is present and can be exploited to create multiple dimensions for communication. In Fig. 6, two Bases 152A and 152B with antenna arrays 55 communicate with Remote Units 170A and 170B that also possess antenna arrays 55. In this case, the composite channel is defined as the MIMO channel between the antennas of the two Bases 152A and 152B and the antennas of the Remote Units 170A and 170B. Note that this channel includes direct line of sight paths 155B and 153B as well as the reflected paths 155A, 155C, 153A, 153C, and 153D. By virtue of the spatial separation between two Bases 152A and 152B, even if the reflected paths are insignificant or nonexistent, this channel contains multipath that can be exploited using the invention. In addition, the channel from the antennas of the two Bases to the antennas of one Remote is again a matrix channel, with rank greater than one, within each SOP bin so that multiple parallel dimensions for transmission may be created. In these types of applications, the present invention provides for the ability to reduce interference radiate to unintentional receivers. Furthermore, the present invention provides the capability of reducing the detrimental effects of received interference from unintentional transmitters.

[0065] Thus it can be seen that multiple transmitter antenna elements or multiple antenna elements may be either co-located or be found at disparate locations. The following symbol channel model applies to all of the above multipath radio propagation cases illustrated by Figs. 4-6. The channel impulse response includes the effects of the propagation environment, as well as the digital pulse shaping filters used in TSFP 30 and RSFP 140, the analog filters used in Modulation & RF System 40 and Demodulation & RF System 120. Due to the difference in propagation delay between the various multipath components combined with the time domain response of the RF and digital filter elements, a single symbol transmitted into the channel is received as a collection of delayed copies. Thus, delayed and scaled versions of one symbol interfere with other symbols. This self interference effect is termed intersymbol interference or ISI. The delay spread parameter, denoted by ν , is the duration in symbol periods of the significant portion of the channel impulse response.

[0066] As the transmitted symbol rate is increased or as the physical geometries in the channel become larger, the delay spread can become so large that conventional space-time processing systems become highly complex. An advantage of the present invention is that the signal processing complexity is relatively low even when the delay spread becomes extremely large. This allows for the economical application of MIMO space-frequency processing techniques at high digital data rates. This efficient use of signal processing comes about because the invention allows the space-time channel to be treated as a set of substantially independent spatial subchannels without sacrificing channel capacity. In contrast, conventional approaches either attempt to equalize the much more complex space-time channel or alternatively sacrifice capacity.

[0067] The channel is modeled as time-invariant over the time spanned by a burst of N data symbols, but varying from one burst to another. This block time invariant assumption produces a channel model that is sufficiently accurate for channels wherein the block duration is short compared to the channel fading, or $(N + 2\nu)T \ll \Delta_B$, where Δ_B is the correlation interval¹. Other models are available wherein the channel varies continuously, but these models add unnecessary complication to the present discussion. It is understood that rapid time variation in the channel can be another motivation for choosing one of the other SOP alternatives in the presence of fading rates that are rapid with respect to the burst frequency. One skilled in the art will be aware of the pertinent issues for a given application. For example, Orthogonal Frequency Domain Multiplexing (OFDM) is an SOP composed of an IFFT and cyclic prefix as the transmitter SOP, and an FFT as the receiver SOP. With OFDM, one pertinent issue is frequency domain inter-carrier interference (ICI), which can occur in OFDM systems with extremely rapid fading. Such pertinent issues shape the appropriate choice of channel models for various SOP basis functions.

[0068] With this background discussion, it can be verified by one skilled in the art that the relationship between the transmitted burst of baseband symbols and the received burst of baseband samples may be adequately expressed as the space-time equation,

$$\mathbf{x}(k) = \mathbf{G}(k)\mathbf{z}(k) + \mathbf{l}(k),$$

where the index k represents bursts. The composite channel output for one burst of data, $\mathbf{x}(k)$, is written with all time samples appear in sequence for every receive antenna 1 to M_R ,

$$\mathbf{x}(k) = [x_1(1) \cdots x_1(N + \nu - 1) \cdots x_{M_R}(1) \cdots x_{M_R}(N + \nu - 1)]^T.$$

¹ The correlation interval here is defined as the time period required for the fading parameter time-autocorrelation function to decrease to some fraction of the zero-shift value.

Likewise, the input symbol vector is written,

$$\mathbf{z}(k) = [z_1(1) \cdots z_1(N) \cdots z_{M_T}(1) \cdots z_{M_T}(N)]^T.$$

The quantity $\mathbf{l}(k)$, defined the same as $\mathbf{x}(k)$ and $\mathbf{z}(k)$, represents both noise and interference. The MIMO channel matrix, $\mathbf{G}(k)$, is composed of single-input single-output (SISO) sub-blocks,

$$\mathbf{G}(k) = \begin{bmatrix} \mathbf{G}_{1,1}(k) & \cdots & \mathbf{G}_{1,M_T}(k) \\ \vdots & \ddots & \vdots \\ \mathbf{G}_{M_D,1}(k) & \cdots & \mathbf{G}_{M_D,M_T}(k) \end{bmatrix} \in \mathbb{C}^{M_D \times (N+M)M_D}. \quad (1)$$

Furthermore, each of the SISO sub-blocks, $\mathbf{G}_{ij}(k)$, is a Toeplitz matrix describing the input-output relationship between the transmitted symbol burst and the received symbol burst for antenna pair (i,j) . This MIMO space-time channel is illustrated by Fig. 7, which shows SISO sub-blocks 180A-D and the addition of interference for each receiver sample.

Space-Frequency Processing

[0069] Embodiments of the present invention uses space-frequency processing at either the transmitter or receiver, or both, to create effective communication systems in wireless channels. Generally, the processing substantially eliminates the ISI caused by the channel correlation across space (antenna correlation) and time (delay spread). This processing greatly simplifies the design of the remaining functions that comprise a complete communication system, including coding and modulation. Furthermore, the processing approach is based upon a capacity-achieving structure for the MEMO wireless communication channel. Space-frequency processing is composed of one or more of the following: an SOP, a transmit spatial processor, and a receive spatial processor.

Substantially Orthogonalizing Procedure

[0070] The use of an SOP in a SISO channel is considered first in order to illustrate the invention's ability to eliminate ISI across space and time. The SOP is composed of signal processing operations implemented at both the transmit and receive sides of the channel. This is illustrated in Fig. 8 where a Transmitter SOP processor 190 and a Receiver SOP processor 200 jointly perform a complete SOP. The SOP ensures that the N input symbols, in bin 1 through bin N , are transmitted through the channel in such a way that each output symbol is substantially influenced by only the input symbol of the same frequency bin. For example, the input symbol in bin 1 is the only symbol to have substantial influence on the output symbol value in bin 1.

[0071] This concept generalizes to the MIMO system as shown in Fig. 9. For the MIMO system, each transmitter antenna 51 is preceded by one of M_T identical Transmitter SOP processors. Likewise, each receiver antenna 111 precedes one of M_R identical Receiver SOP processors. Hence, the processing path for any transmitter-receiver antenna pair contains a jointly performed complete SOP. In other words, there exist $M_R M_T$ SISO SOPs in the MIMO system. By exploiting the property of superposition, this collection of SISO SOPs comprise a MIMO SOP where any two symbols communicated in different bins exhibit substantially reduced crosstalk, irrelevant of the antennas by which the symbols were transmitted and received. Therefore, the SOP establishes N substantially independent MIMO spatial channels.

[0072] Many different SOP implementations exist, including an IFFT-FFT pair, a bank of multiple narrow-band filters, and generalized wavelet transform pairs. One advantageous example of an SOP is the use of a frequency transform combined with a burst cyclic prefix application procedure processor 207, as shown in Fig. 10. There is also a cyclic prefix removal procedure processor 206 at the receive end. When the frequency transform is an IFFT-FFT pair 205 and 208 as shown in Fig. 10, this particular SOP is commonly referred to as discrete orthogonal frequency division multiplexing (OFDM). Hence, this embodiment of the invention combines the OFDM SOP with multiple input antennas, or multiple output antennas, or both multiple input and multiple output antennas. The present embodiment is thus termed matrix-OFDM (MOFDM).

[0073] The analysis presented for MOFDM will have a substantially similar form as other choices for the SOP. These alternative embodiments have certain advantages and drawbacks as compared to the OFDM SOP. For example, the multi-band SOP does not completely eliminate ISI, but it is more robust to certain types of narrow-band interfering signals because the interference can be more confined within a given SOP bin as compared to the OFDM SOP. The

ISI that can be present in the multi-band SOP could make it advantageous to use pre-equalization or post-equalization structures in conjunction with the spatial processing within a given SOP bin. While this complicates the spatial processing, the complexity drawback may be outweighed by other requirements such as robustness to interference or the need to separate the SOP bins by relatively large frequency separation. Only the OFDM SOP will be analyzed in detail herein and it will be understood that one may exploit the other SOP choices as needs dictate.

[0074] As depicted in Fig. 10, the exemplary SOP operates in the following fashion. The symbols from the transmit spatial pre-processor, $z_f(n)$, considered to be in the frequency domain, are organized into M_T vectors of N complex symbols. Each of these vectors is then converted to the time-domain using an N -point inverse-fast-Fourier-transform (IFFT) procedure 205. Each of the parallel M_T time-domain sequences has a cyclic prefix added to the beginning, so that the last v elements in the IFFT output sequence form a pre-amble to the N -element IFFT output. The cyclic prefix operation is given by:

$$[z(1) \cdots z(N)]^T \mapsto [z(N-v+1) \cdots z(N) z(1) \cdots z(N)]^T$$

The application of the cyclic prefix is performed by cyclic prefix application procedure processor 207. For each antenna, the $(N+v)$ -length sequences are passed to the RF transmit chain for D/A conversion and modulation.

[0075] Likewise, each RF receiver chain produces a sampled sequence of length $N+v$. Cyclic prefix removal procedure processors 206 remove the cyclic prefix from each sequence by discarding the first v data symbols, resulting in M_R vectors of N complex symbols. Each of these M_R sequences is then processed with an N -point fast-Fourier-transform (FFT). These symbols are then passed to the receiver spatial processor.

[0076] The effect of the SOP is to substantially remove the ISI between any two symbols assigned to different bins, for any pair of transmit and receive antennas. Therefore, for each IFFT-FFT bin n , the received signal values for each antenna, $x(n)$, are related to the transmitted frequency-domain symbols, $z(n)$, through the expression,

$$x(n) = H(n)z(n) + l(n) \quad \forall n \quad (10)$$

where $x(n)$ is a complex M_R -element vector at SOP bin n , $z(n)$ is a complex M_T -element symbol vector at bin n , and $l(n)$ is the interference and noise at all receive antennas for bin n . Note that a time index is not included in the above equation since it is assumed that channel is time-invariant over the length of a burst. The spatial sub-channels, $H(n)$, are M_R by M_T element matrices that describe the spatial correlation remaining in the wireless channel after the SOP. For the MIMO case, each SOP bin may be characterized by a matrix of complex values, with each value representing the path gain from a given transmit antenna element to a given receive antenna element in that particular SOP bin.

[0077] To understand the result given by Equation (10), it is instructive to show how the SOP pre-processor and post-processor acts upon the time-domain channel. The MIMO time-domain channel, $G(k)$, contains $M_R M_T$ Toeplitz matrices that describe the time-domain input-output behavior of each antenna pair (see eq. 1). This channel formulation is depicted in Fig 10. It is well known that by adding a cyclic prefix at the transmitter and subsequently removing the prefix at the receiver, a Toeplitz input-output matrix is transformed into a circulant input-output matrix (the i th row is equal to the j th row cyclicly shifted by $i-j$ elements). Therefore, the each G_{ij} in Fig. 10 is transformed into a circulant \tilde{G}_{ij} . The MIMO circulant matrices are delimited in Fig. 10 by \tilde{G} .

[0078] This particular class of SOP exploits the fact that any circulant matrix can be diagonalized by a predetermined matrix operator. One such operator is a matrix of the FFT basis vectors. That is, for any circulant matrix \tilde{G} ,

$$D = Y \tilde{G} Y^H$$

where D is some diagonal matrix and the scalar elements of Y are,

$$y_{mn} = \frac{1}{\sqrt{N}} e^{-j2\pi mn/N}$$

Applying M_T IFFT operations at the transmitter and M_R FFT operations at the receiver is described mathematically by a pre-multiplication of a $NM_R \times NM_R$ block diagonal FFT matrix and post-multiplication of a $NM_T \times NM_T$ IFFT matrix. For example, the former matrix is defined,

$$\mathbf{Y}_{(M_D)} = \begin{bmatrix} \mathbf{Y} & & \mathbf{0} \\ & \ddots & \\ \mathbf{0} & & \mathbf{Y} \end{bmatrix}.$$

Therefore, including the transmitter IFFT and receiver FFT operations, the input-output relationship is described by

$$\mathbf{Y}_{(M_D)} \tilde{\mathbf{G}} \mathbf{Y}_{(M_T)}^H = \begin{bmatrix} \mathbf{D}_{1,1} & \cdots & \mathbf{D}_{1,M_T} \\ \vdots & \ddots & \vdots \\ \mathbf{D}_{M_D,1} & \cdots & \mathbf{D}_{M_D,M_T} \end{bmatrix},$$

where \mathbf{D}_{ij} is the diagonal matrix containing the SOP bin strengths for the antenna pair (i,j) . Pre-multiplication and post-multiplication by permutation matrices \mathbf{P}_T and \mathbf{P}_R represents the collection of all antenna combinations that correspond to a common frequency or SOP bin. This collection process, depicted in Fig. 10, results in a block diagonal matrix that relates the inputs and outputs:

$$\mathbf{P}_R \mathbf{Y}_{(M_D)} \tilde{\mathbf{G}} \mathbf{Y}_{(M_T)}^H \mathbf{P}_T = \begin{bmatrix} \mathbf{H}(1) & & \mathbf{0} \\ & \ddots & \\ \mathbf{0} & & \mathbf{H}(N) \end{bmatrix},$$

which is equivalent to Equation (10).

Spatial Processing

[0079] The spatial processing procedure is now considered. Since the SOP establishes N MIMO spatial channels that are substantially independent from one another (Equation 10), one can consider the spatial processing within each bin separately. Representative application of spatial processing to frequency bin 1 will be considered as shown in Fig. 11 at the transmitter and Fig. 12 at the receiver. Fig. 11 shows M symbols: $z(1,1)$ through $z(1,M)$. The notation $z(n,m)$ refers to the symbol transmitted in bin n and spatial direction m . These M symbols will jointly occupy frequency bin 1. Each TSW 210A-C applies a weight vector to the symbol appearing at its input, and the elements of the resultant vector are routed to M_T summing junctions 211. One may consider the TSWs as being multipliers taking each input symbol and multiplying it by a vector that corresponds to a spatial direction in M_T -space. Furthermore, the M vectors define a subspace in M_T -space. Note that the TSW vectors are considered to be column vectors in the discussion that follows. When these M vectors are collected into a matrix, the result is an input orthogonalizing matrix or beneficial weighting matrix for that bin. For each input bin, a vector including symbols allocated to subchannels corresponding to the bin is multiplied by the input orthogonalizing matrix to obtain a result vector, elements of the result vector corresponding to the various transmitter antenna elements. Together, the TSWs 210A-C make up one embodiment of a Transmit Spatial Processor (TSP) 230.

[0080] Each RSW 220A-C accepts M_R inputs, one from each receiver antenna path. Within the m^{th} RSW, a weight vector is applied to the inputs (i.e. an inner-product is performed) thereby producing a received signal sample $x(1,m)$:

$$\mathbf{x}(1,m) = \mathbf{u}(1,m) \begin{bmatrix} x_1(1) \\ \vdots \\ x_{M_R}(1) \end{bmatrix},$$

where $\mathbf{u}(1,m)$ is the RSW for bin 1 and spatial direction m . Similar to a TSW, a RSW vector has an associated direction

in M_R -space. Each RSW may also be considered to be a multiplier. This vector is considered to be a row vector. When these M RSW vectors are collected into a matrix, the result is an output orthogonalizing matrix or beneficial weighting matrix for that bin. When a vector including symbols in a particular output bin produced by the SOP for each receiver antenna is multiplied by the output orthogonalizing matrix, the result is a vector including symbols received in that bin for various spatial directions. Together, the RSWs 220A-220C represent one embodiment of a Receive Spatial Processor (RSP) 240.

[0081] Through proper choice of the weight vectors applied via the TSWs and RSWs, the M spatial directions can be made substantially orthogonal to one another. The result is that the received signal sample $x(1,m)$ depends only upon input symbols $z(1,m)$ and not the $M-1$ other input symbols for SOP bin 1. Methods for selecting the TSP and RSP weight vectors are described in detail below.

[0082] The spatial processing described above can be applied to the other $N-1$ frequency bins in addition to frequency bin 1. The block diagram for such a system is depicted in Fig. 13 for the transmitter and Fig. 14 for the receiver. SOP processors 190 and 200 ensure that the frequency bins remain substantially orthogonal to one another while TSP 230 and RSP 240 ensure that M substantially orthogonal spatial channels exist within each frequency bin. The net result is that NM substantially parallel subchannels are constructed within the MIMO communication system. In other words, the combination of SOP processors 190 and 200, TSP 230, and RSP 240 create a set of substantially independent space-frequency subchannels,

$$x(n,m) = H(n,m)z(n,m) + l(n,m) \quad \forall n,m.$$

This simultaneous substantial orthogonalization of space and frequency can result in a significant increase in spectral efficiency since multiple data streams are being communicated through the channel. Note that the number of substantially independent subchannels possible, in the multipath case, is equal to the number of SOP bins multiplied by the number of transmit antennas or the number of receive antennas, whichever is smaller. Therefore, the total number of space-frequency subchannels is less than or equal to $N \min(M_T, M_R)$, when multipath is present.

[0083] An exemplary set of TSWs and RSWs are derived from the singular value decomposition (SVD) of the spatial channel matrix for each bin,

$$H(n) = U(n)\Sigma(n)V(n)^H.$$

The input singular matrix, $V(n)$, contains M_T column vectors that define up to M_T TSWs for bin n . Likewise, the output singular matrix, $U(n)$, contain M_R column vectors that when Hermitian transposed, define up to M_R RSW row vectors for bin n . The TSWs and RSWs for other bins are determined in the same fashion, through an SVD decomposition of the spatial matrix for that bin. Using this spatial processing, substantially independent multiple streams of symbols can be transmitted and received. The strength of each subchannel is equal to one of the elements of the diagonal matrix Σ . These subchannels strengths will vary. Therefore, the subchannels will have varying signal to noise ratios and information capacity. For this reason, it may be preferable to transmit and receive only on a subset of the possible subchannels, or $M < \min(M_T, M_R)$. For example, it may be improvident to use processing complexity on the weakest subchannels that may have a very small information carrying capacity. In this case, spatial processing is used to increase the received power of one or more parallel symbol streams. It may also be preferable to use coding techniques to leverage strong subchannels to assist in the use of weaker subchannels. It may also be preferable to allocate either bits or transmit power among the subchannels to maximize the amount of information communicated.

[0084] The exemplary spatial processing described above requires cooperation between the transmitter and receiver to effectively orthogonalize the spatial channel for each bin. Alternatively, this orthogonalization can be accomplished at only one end of the link. This can be advantageous when one end of the link can afford more computational complexity than the other end. In addition, spatial orthogonalizing at one end can be advantageous when the channel model is known only at that end.

[0085] Consider the case where the orthogonalization is done at the receiver. Symbols are transmitted along directions defined by some set of TSWs, $v(n,m)$. When M TSWs corresponding to the same bin are collected into a matrix $V(n)$, the composite spatial channel is,

$$H'(n) = H(n)V(n).$$

This composite channel describes the MIMO channel in bin n from the M -inputs to M_R outputs. The spatial processing at the receiver can substantially orthogonalize this composite channel, $H'(n)$, by applying appropriate RSWs even if

the transmitter does no spatial processing. Let these RSWs be defined as the row vectors of the weighting matrix, $\mathbf{W}_R(n)$.
[0086] Two exemplary methods for determining $\mathbf{W}_R(n)$ are referred to as the zero-forcing (ZF) solution and minimum-mean-square-error (MMSE) solution. In the ZF approach, the weighting matrix is the pseudo-(left)-inverse of the composite channel,

$$\mathbf{W}_R(n) = \mathbf{H}'(n)^\perp.$$

This results in,

$$\mathbf{W}_R(n)\mathbf{H}'(n) = \mathbf{I},$$

where the identity matrix is M by M . Hence, the ZF solution, not only orthogonalizes the spatial channel for bin n , but it equalizes the strengths of each resulting subchannel. However, the signal-to-noise ratio for the various subchannels can vary widely. One skilled in the art will recognize that the ZF solution can result in amplification of the interference and noise unless the composite channel, $\mathbf{H}'(n)$, is nearly orthogonal to begin with.

[0087] An MMSE solution, on the other hand, does not amplify noise. For the MMSE approach, the weight, $\mathbf{W}_R(n)$, satisfies,

$$\min_{\mathbf{W}_R(n)} E \left\{ \left\| \mathbf{W}_R(n)\mathbf{x}(n) - \mathbf{z}(n) \right\|^2 \right\},$$

or,

$$\mathbf{W}_R(n) = \mathbf{R}_{\mathbf{z}(n)\mathbf{x}(n)} \mathbf{R}_{\mathbf{x}(n)}^{-1},$$

where $\mathbf{R}_{\mathbf{x}(n)}$ is the covariance matrix for $\mathbf{x}(n)$ and $\mathbf{R}_{\mathbf{z}(n)\mathbf{x}(n)}$ is the cross-covariance between $\mathbf{z}(n)$ and $\mathbf{x}(n)$. Using,

$$\mathbf{x}(n) = \mathbf{H}'(n)\mathbf{z}(n) + \mathbf{l}'(n),$$

and the fact that $\mathbf{R}_{\mathbf{z}(n)} = \sigma_z^2 \mathbf{I}$, results in the MMSE weight,

$$\mathbf{W}_R(n) = \mathbf{H}'(n)^H \left(\mathbf{H}'(n)\mathbf{H}'(n)^H + \frac{1}{\sigma_z^2} \mathbf{R}_{\mathbf{l}'} \right)^{-1}.$$

Note that when $\mathbf{l}(n)$ is spatially white noise, then $\mathbf{R}_{\mathbf{l}'} = \sigma_l^2 \mathbf{I}$.

Similarly to the above orthogonalization at the receiver, the channel can be orthogonalized at the transmit end only. For this to occur, the transmitter is required to have knowledge of the RSWs to be used by the receiver. In a TDD channel, where the channel exhibits reciprocity, these RSWs can be learned when that transceiver uses TSW directions equal to the RSW directions. Alternatively, the receiver may not do any spatial processing, so the transmitter is responsible for spatial orthogonalization.

In this case, the composite channel is

$$\mathbf{H}'(n) = \mathbf{U}(n)\mathbf{H}(n),$$

where the matrix $\mathbf{U}(n)$ is composed of the RSW row vectors, $\mathbf{u}(n,m)$. This composite channel describes the MIMO channel in bin n from M_T inputs to M outputs. Similar to the previous case, the transmitter can substantially orthogonalize this composite channel, $\mathbf{H}'(n)$, by applying appropriate TSWs. These TSWs are the column vectors of the weighting matrix, $\mathbf{W}_T(n)$.

[0088] The transmit weighting can be determined using the ZF or the MMSE approach. In the ZF approach, the weighting matrix is equal to the pseudo-(right)-inverse of $\mathbf{H}'(n)$. The MMSE solution satisfies

$$\min_{\mathbf{w}_T(n)} E \left\{ \left\| \mathbf{H}'(n) \mathbf{W}_T(n) \mathbf{z}(n) + \mathbf{I}'(n) - \mathbf{z}(n) \right\|^2 \right\},$$

An important simplification to the general space-frequency processing technique is the use of only one spatial direction for each bin of the SOP. This case is depicted in Fig. 15 for the transmitter and Fig. 16 for the receiver. In this case, only N subchannels are created. The N input symbols, $z(1,1)$ through $z(N,1)$, are processed by N TSWs 210A-B that weight and allocate these N symbols among the M_T identical SOP processors 190. At the receiver, the antenna samples are processed by M_R SOP processors 200. The M_R SOP outputs corresponding to a common bin are weighted and combined in N RSWs 220A-B. With N such weightings, the result is N outputs, $x(1,1)$ through $x(N,1)$, of the N substantially orthogonal subchannels.

[0089] When only one spatial direction is used in the TSP and RSP, one exemplary choice for the particular weightings are the TSW and RSW directions that result in maximum subchannel strength. This maximizes the signal-to-noise ratio (SNR) of the received signals, $x(1,1)$ through $x(N,1)$. In this case, the optimal weightings should satisfy,

$$\max_{\mathbf{u}(n), \mathbf{v}(n)} \left| \mathbf{u}(n) \mathbf{H}(n) \mathbf{v}(n) \right|^2,$$

with the implicit constraint on the size (2-norm) of both the RSW weight $\mathbf{u}(n)$ and the TSW weight $\mathbf{v}(n)$. To determine the solution to this optimization problem, consider the SOP outputs for bin n when a single TSW, $\mathbf{v}(n,1)$, is used,

$$\begin{bmatrix} x_1(n) \\ \vdots \\ x_{M_R}(n) \end{bmatrix} = \mathbf{H}(n) \mathbf{v}(n,1) z(n,1) = \mathbf{h}(n) z(n,1).$$

[0090] The quantity $\mathbf{h}(n)$ is referred to as the received channel vector. A channel identification technique is used to determine the received channel vector. Therefore, the optimal RSW weight is equal to the Hermitian of the received channel vector, $\mathbf{h}(n)$,

$$\mathbf{u}(n) = \mathbf{h}(n)^H.$$

Note that this is true regardless of the particular value of $\mathbf{v}(n)$. The optimal TSW direction, on the other hand, satisfies,

$$\max_{\mathbf{v}(n)} \mathbf{u}(n) \mathbf{H}(n) \mathbf{v}(n) = \max_{\mathbf{v}(n)} \mathbf{v}(n)^H \mathbf{H}(n)^H \mathbf{H}(n) \mathbf{v}(n),$$

where the optimal RSW direction has been used. The optimal TSW for bin n is equal to the scaled maximum eigenvector of the matrix $\mathbf{H}(n)^H \mathbf{H}(n)$. One skilled in the art will recognize that the optimal RSW is also equal to the scaled maximum eigenvector of $\mathbf{H}(n) \mathbf{H}(n)^H$.

[0091] A further advantageous simplification of the above techniques is the use of one or more common TSW and RSW directions for all bins. In other words, every bin has the same TSW and RSW weights. These weight vectors may also consider delay elements. In one embodiment, these weights are determined to maximize the SNR of the received signals, averaged over frequency n . This is depicted in Fig. 17 for the transmitter and Fig. 18 for the receiver. Consider this embodiment with one spatial direction. In this case, the TSW and RSW weights satisfy,

$$\max_{\mathbf{u}, \mathbf{v}} E_n \left[\mathbf{u}^H \mathbf{H}(n) \mathbf{v} \right].$$

50

Note that the expectation operator, E_n , represents averaging over SOP bins. This averaging could also be done over multiple bursts in addition to frequency. The solution to this problem is when \mathbf{v} is equal to the maximum eigenvector of

$$\mathbf{R}_d = E_n \{ \mathbf{H}^H(n) \mathbf{H}(n) \},$$

51

5 and \mathbf{u} is equal to the maximum eigenvector of the covariance matrix formed from averaging the outer product of the receive vector channel,

$$\mathbf{R}_h = E_n \{ \mathbf{h}(n) \mathbf{h}(n)^H \}.$$

52

The quantity \mathbf{R}_d is the spatial covariance matrix that describes preferable directions to transmit to the desired receiver, a desired subspace.

[0092] This technique can be generalized to the case where multiple directions are utilized. In this case, M TSWs and M RSWs are determined to maximize the average (over bin) SNR received through the M spatial directions. The M spatial directions will not necessarily be orthogonal to each other. Therefore, there will be spatial crosstalk in the received symbols. Multidimensional encoding and decoding techniques discussed below can then achieve a multiplicative rate increase in the presence of such crosstalk.

[0093] Alternatively, the receiver can spatially orthogonalize the subchannels by further weighting of the M outputs from the RSWs. The composite spatial channel at bin n , with the RSWs and TSWs included is

$$\mathbf{H}'(n) = \mathbf{U} \mathbf{H}(n) \mathbf{V},$$

53

25 where the matrix \mathbf{U} is made up rows equal to the RSW directions and \mathbf{V} is a matrix with columns equal to the TSW directions. Since \mathbf{U} and \mathbf{V} were determined based on an average SNR criterion for all bins, the composite matrix $\mathbf{H}'(n)$ will not be diagonal. Hence, the receiver can apply the additional weight, $\mathbf{W}_R(n)$, to orthogonalize $\mathbf{H}'(n)$. Alternatively, the transmitter can use the additional weight, $\mathbf{W}_T(n)$, to spatially orthogonalize the composite channel. Exemplary solutions for these weightings are the joint SVD, the ZF and MMSE. The advantage of this approach is that the processing required to adapt all N SOP bin matrix channels may be substantially higher than the processing complexity to adapt the average TSP and RSP.

[0094] The rejection and prevention of interference can be accomplished in conjunction with the space-frequency processing discussed above. This is especially useful when the number of spatial directions used for communication is less than the number of antennas. This case occurs when weak spatial directions are not utilized or when the number of antennas at the receiver and transmitter are not the same. In either case, one or both ends of the communication link have extra spatial degrees of freedom to use for the purpose of mitigating interference.

[0095] The amount of interference arriving at an antenna array can be quantified by the interference covariance matrix,

$$\mathbf{R}_I(n) = E \{ \mathbf{l}(n) \mathbf{l}(n)^H \},$$

40 where $\mathbf{l}(n)$ is the M_R length interference plus noise vector received in SOP bin n . This matrix defines an undesired interference plus noise subspace in M_R -space for bin n . The interference plus noise energy that contaminates a particular received subchannel symbol with bin n and spatial direction m , is equal to,

$$\mathbf{u}^H(n, m) \mathbf{R}_I(n) \mathbf{u}(n, m),$$

50 where $\mathbf{u}(n, m)$ is the combining weight vector for the RSP(n, m). An advantageous interference rejection technique is then to "whiten" the effect of the interference across the spatial directions, so that the interference is minimized and spread evenly across all spatial directions used. Therefore, each of the RSP weighting vectors are modified by the matrix $\mathbf{R}_I^{-1/2}(n)$,

$$\mathbf{u}'(n, m) = \mathbf{u}(n, m) \mathbf{R}_I^{-1/2}(n).$$

[0096] Alternatively, the RSP weighting vectors are the vectors of the output singular matrix, $\mathbf{U}'(n)$, from the SVD of

the modified spatial channel,

$$R_i^{-1/2}(n)H(n) = U'(n)\Sigma'(n)V'(n)^H.$$

Note that a very useful simplification of the above interference rejection technique is to average the interference covariance matrix over all N bins and possibly a set of bursts to arrive at an average spatial interference covariance matrix, R_i , that is independent of bin n. In this case, every RSP combining vector is modified in the same way due to interference. This approach can significantly reduce the amount of computations needed to determine R_i and $R_i^{-1/2}$. Note that it is often beneficial to add a scaled matrix identity term to estimates of the interference covariance matrix to reduce the sensitivity of these interference mitigation approaches to covariance estimation errors.

[0097] Similar interference mitigation techniques can be advantageously employed at the transmitter to reduce the amount of interference radiated to unintentional receivers. In the TDD channel, reciprocity in the radio link allows the undesired receive interference subspace in each SOP bin to be accurately used to describe the transmitter subspace. That is, the amount of interference transmitted to unintentional receivers is

$$v^H(n,m)R_i(n)v(n,m), \quad 60$$

where $v(n,m)$ is the transmit weight vector for the TSW(n,m). An optimal interference reduction approach is then to minimize and "whiten" the transmitted interference across spatial directions. In the same fashion as the receiver case, the TSW vectors are modified by the matrix $R_i^{-1/2}(n)$. Alternatively, the TSP weight vectors are the vectors of the input singular matrix $V'(n)$ from the SVD of the modified spatial channel,

$$H(n)R_i^{-1/2}(n) = U'(n)\Sigma'(n)V'(n)^H. \quad 61$$

[0098] Again, a significant simplification occurs when the interference covariance matrix is determined by averaging over frequency or SOP bins. It is especially advantageous to average over SOP bins in a frequency-division-duplex (FDD) system, where significant averaging of the receive covariance matrix results in a good estimate of the transmit covariance, even though instantaneous channel reciprocity does not hold.

[0099] Interference rejection at the receiver and interference reduction at the transmitter are done together by simply combining the two techniques outlined above. In this case, the RSP vectors and TSP vectors are contained in the input and output matrices of the SVD of,

$$R_{i,R}^{-1/2}(n)H(n)R_{i,T}^{-1/2}(n).$$

[0100] As outlined previously, it can be advantageous to use the same TSWs and RSWs for all bins. This approach can be combined with interference mitigation by the determining the transmit and receive weight vectors that maximize average power delivered to the receiver of interest, while at the same time, minimizing power delivered to other undesired receivers. There are various optimization problems that can be posed to determine these TSP or RSP directions, each involving the desired receiver covariance matrix and the undesired covariance matrix. For example, one TSP problem is

$$\max_v v^H R_d v \quad \text{such that} \quad v^H R_i v \leq P_i \quad \text{and} \quad v^H v \leq P_T.$$

That is, a TSP direction is chosen for all SOP bins that transmits the maximum amount of power to the desired receiver while maintaining a transmit power limit, P_T , and a transmitted interference limit, P_i . For this particular problem, the TSP direction is equal to the maximum generalized eigenvector of the matrix pair $\{R_d, (R_i/P_i + I/P_T)\}$. One example of an effective interference rejecting RSP for all SOP bins is a weighing that maximizes the average received SINR. The RSP that maximizes SINR is the maximum eigenvector of the matrix $R_i^{-1/2} R_d R_i^{-1/2}$.

[0101] One further simplification to the above algorithm is to model the interference and/or the desired covariance as diagonal, or nearly diagonal. When both R_d and R_i are diagonal, the solution to the above optimization problem reduces to the maximal ratio SINR combiner, u, and transmitter, v. It is also sometimes preferable to only consider other subsets of the elements of either the desired or interference covariance matrices.

[0102] One skilled in the art will also recognize that all the TSPs and RSPs can be used when there is only one SOP bin, such as a common frequency.

Space Frequency Coding

[0103] Many of the advantageous space frequency encoding techniques embodied in the invention may be broadly classified in two exemplary categories. The first category involves techniques wherein the spatial matrix channel within each SOP bin undergoes space frequency processing at the transmitter, or the receiver or both, resulting in a substantially independent set of one or more parallel communication subchannels within each SOP bin. The objective of the encoder and decoder in this case is to appropriately allocate the transmitted information among multiple independent space-frequency subchannels using interleaving, power and bit loading, or both. The second category of space frequency encoding involves transmitting and receiving one or more symbol sequences in each SOP bin using one or more transmitter and receiver weight vector combinations that are not necessarily intended to create independent spatial subchannels within each SOP bin. This results in significant cross-talk between each symbol stream present at the receiver output. A decoder then uses knowledge of the equivalent matrix channel within each SOP bin, and knowledge of the set of possible encoder sequences to estimate the encoder symbol sequence that gave rise to the cross-talk rich output SOP bin vector sequence. The main differentiating feature between the first approach and the second approach is the presence or lack of spatial processing that results in substantially orthogonal spatial subchannels within each SOP bin. Both approaches have the advantageous ability to multiply the data rate that can be achieved in MIMO channels with multipath.

Coding for Substantially Orthogonal Space-Frequency Subchannels

[0104] In applications where the spatial channels are processed to achieve multiple substantially independent spatial subchannels within each SOP bin, an advantageous embodiment of the invention involves encoding the input data sequence into a digital symbol stream that is then routed in various beneficial ways through the available parallel space frequency subchannels. Fig. 22 depicts a preferred embodiment. This embodiment involves distributing the symbol outputs of a single encoder among all of the available space frequency subchannels. Several known coding schemes that can be combined effectively with space frequency processing to distribute information transmission over the space and frequency dimensions of a communication channel. This discussion assumes estimation of the MIMO channel by transmitting a series of training symbol sequences from each antenna element as discussed herein. The discussion further assumes that the receiver and transmitter either share the information required to decompose the channel into parallel sub-channels, or the TDD techniques discussed herein are used to do the same.

[0105] Referring again to Fig. 22, the preferred embodiment exploits a three layer coding system. The first layer of coding includes the combination of transmitter TSWs 210A through 210B, Transmitter SOP processors 190, receiver SOP processors 200, and receiver RSWs 220A through 220B. This first layer of coding performs the spatial processing. The second layer of coding includes a Trellis Encoder and Interleaver (420) at the transmitter in combination with a Deinterleaver and ML Detector 430 at the receiver. The third layer code involves Reed Solomon (RS) Encoder 410 at the transmitter in combination with an RS Decoder 440 at the receiver. The bit level RS coding occurs prior to the trellis encoding and the Reed Solomon codeword detector acts upon the bit sequence from the ML detector. The fourth layer of coding involves an ARQ code that recognizes Reed Solomon codeword errors at the receiver in the Receiver ARQ Buffer Control 450 and requests a codeword retransmission from the Transmitter ARQ Buffer Control 400. The retransmission request is made through a Reverse Link Control Channel 460. The reverse control channel is a well known radio system concept and will not be discussed herein. This combination of coding techniques and space frequency processing is preferable because it provides for a rich combination of space and frequency diversity and it is capable of obtaining very low bit error rates. The detailed operation of the RS encoder and decoder, as well as the ARQ system is well known to one skilled in the art. Following this discussion, it will be clear to one skilled in the art that other combinations of one or more of these four coding elements may be employed with advantageous results in various applications.

[0106] The trellis coding step may be substituted with CBM-QAM or a turbo code. Similarly, the Reed-Solomon code may be substituted with a block code, or with an error checking code such as a CRC code. The transmitter end would then include the necessary encoder and the receiver end would include the necessary decoder.

[0107] There are at least two basic methods for employing trellis coding to distribute information among substantially independent space frequency subchannels. One method is adaptive encoding that modifies the bit and power loading for each subchannel according to its quality. The second method involves maintaining constant power and bit loading for all space frequency subchannels. Both of these methods are discussed below.

Space Frequency Trellis Coding with Orthogonal Spatial Subchannels and Adaptive Power and Bit Loading

[0108] Fig. 22 depicts the coding and interleaving detail for the transmitter and receiver portions of the present embodiment. Encoding and Interleaving system 10 encodes the data into a set of complex symbols. Each of the complex symbols is then allocated to a particular transmitter TSW (210A through 210B). The input to each TSW forms a vector of frequency domain symbols that are fed into the same bin of one or more transmit SOP processors. Each transmitter TSW, possibly in conjunction with a receiver RSW converts the matrix channel within each SOP bin into a set of substantially orthogonal space frequency subchannels using one of the methods discussed herein.

[0109] Fig. 23 displays a more detailed diagram of the encoder and interleaver. An Information Allocation Unit 360 assigns the bits and the transmitter power that will be allocated to each space frequency subchannel. One method for accomplishing this assignment is the so-called gap analysis. In this technique, a particular coset code with an associated lattice structure is characterized by first determining the SNR required to achieve a theoretical capacity equal to the desired data rate. The code gap is then the SNR multiplier required to achieve the target probability of error at the desired data rate. In a parallel channel communication system, this gap can be used to determine the power and bit distributions that maximize data rate subject to a probability of error constraint. With a coding gap of α , the rate maximizing water-filling solution for the space frequency subchannels becomes

$$p(n, m) = \left(\xi - \frac{\sigma_n^2 \alpha}{|\lambda(n, m)|^2} \right)^+$$

where σ_n^2 is the noise power and m is the spatial index and n is the DFT frequency index. The bit allocation per subchannel is then given by

$$b(n, m) = \log \left(1 + \frac{p(n, m) \cdot |\lambda(n, m)|^2}{\alpha \sigma_n^2} \right).$$

After the power and bit loading assignments are accomplished in the Information Allocation Unit, the bits are encoded with a Trellis Encoder 370. It is not possible to achieve infinite bit resolution (granularity) with coset codes. Therefore the gap analysis solution should be modified. Several bit loading algorithms exist to resolve this problem. One method involves rounding down the water filling solution to the nearest available quantization. The granularity of possible bit allocations is determined by the dimensionality of the coset code lattice structure. In the MIMO channel communication structures described herein, the orthogonal constellation dimensions are the complex plane, space, and frequency.

[0110] Fig. 26 illustrates an example of a practical method for bit loading with a trellis encoder that uses a one dimensional QAM symbol constellation. The bit load is adjusted down for a given trellis encoder output symbol by assigning a number of fixed zeros to one or more of the input bits to the encoder. Fig. 26 shows the operation of the trellis encoder and the trellis state diagram for the decoder for four successive symbol transmissions. Four bits are assigned to the first space frequency subchannel. A first subchannel trellis encoder input 350 is assigned 4 bits so Symbol 1 can take on any one of 32 values. There are two bits feeding the convolutional encoder, and two bits feeding the coset select. The ML detector at the receiver uses the trellis state diagram and the channel state information to solve the maximum likelihood recursion. This is efficiently accomplished with the Viterbi algorithm. The trellis code state diagram defines a set of symbol sequence possibilities $\{Z\}$. The space frequency subchannel is denoted $H(n, k)$, for SOP bin n at burst k . The maximum likelihood equation is then given by

$$\{\hat{z}(1)^T, \hat{z}(2)^T, \dots, \hat{z}(N)^T\} = \arg \left\{ \min_{z=\{z(1)^T, z(2)^T, \dots, z(N)^T\}} \sum_{n=1}^N |\hat{H}(n, k)z(n) - x(n, k)|^2 \right\}$$

where $z(n)$ is the symbol hypothesized for SOP bin n . The decoder output state diagram for first space frequency subchannel 340 includes four possible parallel transitions for each trellis branch and all of the trellis branches are possible. The second space frequency subchannel in the sequence is assigned three bits so a second trellis encoder input 352 shows one bit fed into the coset select with two bits still feeding the convolutional encoder. A decoder state diagram 342 for the second space frequency subchannel has only two parallel transitions for each trellis branch but still maintains all trellis branch possibilities. Continuing in succession, a third space frequency subchannel is assigned only two bits to an encoder input 354 so there are no parallel transitions considered by a trellis decoder state diagram 344. In a fourth space frequency subchannel, only one bit is assigned to an encoder input 356 so there are no parallel

transitions and some of the trellis state branches (346) are no longer considered by the decoder. It is understood that Fig. 26 is provided as a graphical aid and is not intended to represent an actual design.

[0111] The maximum Euclidean distance error sequence design metric is one preferable choice for a trellis encoder used with the parallel space frequency channel with this bit and power loading embodiment of the invention. Other code error sequence design metrics that are advantageous in various application conditions include product distance and periodic product distance.

[0112] Referring again to Fig. 23, the output of the encoder is interleaved across the various space frequency subchannels using Interleaving block 260. Typically, the interleaving process distributes the symbols so that symbols that are near one another at the encoder output are well separated in both the SOP bin assignment and the spatial subchannel assignment. This distributes the effects of channel estimation errors and localized frequency domain or spatial domain interference so that the decoder error is reduced. It is understood that the bit and power assignments by Information Allocation block 360 take place with knowledge of the post-interleaved channel strength. It is understood that the encoding and decoding process can begin and end within one burst, or it may take place over a multitude of bursts.

[0113] One skilled in the art will recognize that a multitude of less sophisticated adaptive power and bit loading algorithms can be advantageously applied to a substantially independent set of space frequency subchannels. One example is an algorithm wherein a space frequency subchannel is either loaded with maximum power or no power and the bit distribution may be adjusted in only two increments.

[0114] A second alternative embodiment shown in Fig. 19 includes one encoder for each SOP bin, with the output symbols of each encoder allocated among several spatial subchannels. A third embodiment shown in Fig. 20 involves one encoder for each spatial subchannel, with the output symbols of each encoder distributed among the SOP bins for that spatial subchannel. A fourth embodiment shown in Fig. 21 involves a separate encoder for each available space frequency subchannel.

[0115] It will be clear to one skilled in the art that the channel estimation tools taught herein are very useful in improving the accuracy of the channel estimates used for the bit loading and decoding process.

[0116] One skilled in the art will recognize that many of the other coding techniques for parallel sub-channel bit loading communication systems, not mentioned here, can also be applied to the present invention.

Space Frequency Trellis Coding with Orthogonal Spatial Subchannels and Flat Power and Bit Distribution

[0117] In some cases it is difficult to adaptively load the power and bit assignments for each available space frequency subchannel. For example, the transmitter and receiver may not be able to adapt the loading fast enough to accommodate time domain variation in the channel. In another example, the required feedback from the receiver to the transmitter requires a significant portion of the available reverse link bit rate. Adaptive bit loading may also be overly complicated for certain applications. Thus, it is often advantageous to encode and decode a symbol stream in such a manner that the power and bit allocation is constant for all space frequency subchannels. This is easily accomplished by employing the embodiments depicted in Figs. 22-23, and assigning a constant power and bit allocation to all space frequency subchannels in the Information Allocation block 360.

Space Frequency Coding Without Orthogonal Spatial Subchannels

[0118] In applications where the spatial channels are not processed to achieve substantially orthogonal spatial subchannels within each SOP bin, an advantageous embodiment of the invention involves utilization of a vector maximum likelihood decoder in the receiver to decode a symbol sequence that includes multiple symbols per SOP bin. The vector maximum likelihood detector is capable of determining the transmitted symbol vector in each SOP bin even in the presence of spatial subchannels that contain significant cross-coupling between the channels. The vector maximum likelihood detector uses an estimate of the matrix channel from each SOP bin to decode a sequence of groups of symbols with one group for each SOP bin. The groupings will be referred to here as a multidimensional symbol vector, or simply a symbol vector. The ML detector uses an estimate of the matrix channel that exists in each SOP bin to find the most likely sequence of transmitted encoder vector symbols.

[0119] Fig. 24 depicts a transmitter system wherein multiple space/frequency subchannels are employed without spatial orthogonalization. Fig. 25 depicts a receiver system for this application.

[0120] The bit sequence $b(k)$ is encoded into a sequence of multidimensional symbol vectors in a Bit to Symbol Encoding block 250. Each output of the encoder is an M_0 by 1 complex symbol vector, where M_0 is the number of spatial directions that will be used for transmission. Note that M_0 is preferably chosen to be less than or equal to M_T . A preferable construction of the encoder is a multidimensional trellis encoder. One advantageous metric for designing the trellis encoder constellation and convolutional encoder polynomial will be provided below. Within the previously discussed Symbol Interleaver block 260, the vector symbol sequence is demultiplexed and interleaved with a Symbol

Sequence Demultiplexor 300 and a Transmit Symbol Routing block 310. Transmit Symbol Routing block 310 interleaves the vector symbol sequence so that the elements of a given vector symbol are grouped together and transmitted in one SOP bin. Thus, different vectors are separated by a multitude of SOP bins before transmission, but all elements within the vector symbol share the same SOP bin. The purpose of the interleaver is to distribute the vector symbol sequence so that the fading present in the matrix channels within the SOP bins is randomized at the output of the receiver interleaver. The decoder can recover information associated with symbols that are transmitted through SOP bins that experience a deep fade, provided that the adjacent symbols do not also experience the same fade. Since there is often a high degree of correlation in the fading experienced by adjacent SOP bins, the interleaver makes the fading more random and improves decoder error performance. After interleaving, each element of a vector symbol is assigned to one antenna for the SOP bin assigned to that vector symbol. Transmitter SOP processors 190 perform the transmitter portion of the SOP.

[0121] After the transmitter SOP, it is often advantageous to perform spatial processing with TSP 230. It is understood that the matrix representing the operation of TSP 230, i.e., the Transmitter Weight Matrix, may also be an identity matrix so that no weighting is implemented. It can be beneficial to choose a number of spatial directions that is less than the number of transmitter antennas. In this case, the Transmitter Weight Matrix increases the dimensionality of the time domain vector sequence from the SOP bank. As an example of when it is advantageous to choose a subset of the available transmitter spatial directions, if the receiver has fewer antennas than the transmitter, then it is known that the information capacity of the matrix channels within each SOP bin will not support a number of parallel information subchannels that is greater than the number of receive antennas. This implies that the number of symbols in each transmitted symbol vector, and hence the number of transmitted spatial directions, should not be greater than the number of receiver antennas. As another example, in a Rayleigh fading channel, the smallest singular values of an M_R by M_T matrix channel are on average much weaker than the largest singular value. This implies that the average information capacity contained in the smallest singular value may not justify the extra signal processing complexity required to transmit over that dimension. In both of these cases, it is advisable to choose an advantageous subset of the available transmit spatial directions.

[0122] The transmitter may not have knowledge of the individual channel matrices within each SOP bin but may have knowledge of the covariance statistics of the channel matrices, averaged over frequency, or time, or both. In such cases, the Transmitter Weight Matrix can be optimized to select one or more spatial directions that maximize the average received power for the chosen number of spatial directions. The procedure for optimizing the Transmitter Weight Matrix for this criteria is defined by Equations 50 to 52 and the associated discussion. This is one preferred method of selecting an advantageous set of spatial directions for the Transmitter Weight Matrix. Another advantageous criteria for selecting the transmitter spatial directions is to maximize average received power subject to constraints on the average interference power radiated to unintentional receivers. The procedure for optimizing the Transmitter Weight matrix for this criterion is defined by Equations 60 and 61 and the associated discussion.

[0123] After the time domain signal is spatially processed, the signal is upconverted to the RF carrier frequency using Modulation and RF System 40 before being radiated by Transmit Antennas 51. Referring now to Fig. 25, at the receiver the signal is downconverted and digitized by Receive Antennas 111 and Demodulation and RF System blocks 120. The RSP 240 may then be used to process the time domain signal. The operation of RSP 240 may be characterized by a Receiver Weight Matrix which may be an identity matrix. One embodiment involves optimizing the RSP weights to reduce the number of received signals from M_R to M_0 , which is the number of elements in the transmitted symbol vector and is also the number of transmitted spatial directions. In this case, the Receiver Weight Matrix can be optimized to increase the average signal power in each received spatial direction. The optimization procedure to accomplish this is defined by Equations 50 to 53 and the associated text.

[0124] Channel ID block 130 is used to estimate the matrix channel in each SOP bin. Procedures for channel estimation are described below. Channel state information for each SOP bin is fed into a Symbol to Bit Detector 280 which decodes the symbol sequence after it is passed through a Symbol Deinterleaver 270.

[0125] At the receiver, after de-interleaving the SOP bins, the space-frequency sequence is again converted into a serial symbol stream by Demultiplexor 300. For a given set of spatiotemporal vector symbol sequence possibilities $\{Z\}$, and an estimate, $H(n,k)$, of the channel matrix in each SOP bin n at burst k , the maximum likelihood detector is given by equation (70):

$$\{\hat{z}(1)^T, \hat{z}(2)^T, \dots, \hat{z}(N)^T\} = \arg \left\{ \min_{z \in \{z(1)^T, z(2)^T, \dots, z(N)^T\}} \sum_{n=1}^N \|R_1(n,k)^{-1/2} (\hat{H}(n,k)z(n) - y(n,k))\|_2^2 \right\}$$

where $z(n)$ is the vector representing the code segment hypothesized for SOP bin n , and $R_1(n,k)$ is the estimated noise plus interference covariance matrix for SOP bin n and time k . This equation can be solved efficiently using a vector ML detector. The SOP bin channel matrix estimates are understood to include the effects of the Transmitter

Weight Matrix and the Receiver Weight Matrix. It is understood that the noise pre-whitening step in the ML detector cost function can be substituted by a bank of RSPs that perform the interference whitening as described herein.

[0126] In a Rayleigh fading channel, a desirable metric for designing the trellis code is given by the product of a sum involving the two-norm of vector segments of the trellis code error sequence:

$$\prod_{n=1}^q \|e(n)\|_2^2$$

where q is the number of SOP bins in the error sequence, and $e(n)$ is the vector difference between the true multi-dimensional code symbol segment and the incorrect multi-dimensional symbol code segment for SOP bin n . This code design metric is a generalization on the conventional product distance metric which contains a scalar error entry in the product equation while the new code design metric contains a vector two norm entry in the product equation. It should now be evident that the multidimensional encoder can be realized by either directly producing a vector consisting of a multidimensional QAM symbol with the encoder output or by grouping complex QAM symbols from a one dimensional encoder output into a vector. The vector symbol encoder alternative is preferred in some cases because this approach provides for a larger metric search result and hence a better fading code. After deinterleaving, the decoder that is used at the receiver searches over all possible multidimensional symbols within each SOP bin to maximize Equation 70. It is understood that one skilled in the art will recognize after this discussion that other desirable metrics such as Euclidean distance metrics, metrics designed for Rician fading channels, periodic product distance metrics, and others are straightforward to construct and space-frequency codes can then be determined through well known exhaustive search techniques.

[0127] In either the one dimensional encoder case, or the multidimensional encoder case, the encoder constellation selection and code polynomial search to maximize the metric can be carried out using a number of well known procedures.

[0128] It is possible to improve the performance of the space-frequency coding system described above by using a number of transmitter antennas, or a number of receiver antennas, that is greater than the number of symbols transmitted in each SOP bin. If the number of receiver antennas is greater than the number of symbols in each SOP bin, then simply applying the approach described above is advantageous. If the number of transmitter antennas is greater than the number of symbols transmitted in each SOP bin, then the techniques embodied in Equation 70 are advantageous.

Channel Identification

[0129] The operation of Channel Identification block and Training Symbol Injection block 20 will now be described. The transceiver should determine the MIMO channel in order to form the TSWs and RSWs. For coherent spatial processing and detection, the receiver should obtain an estimate of the channel. We wish to identify the set of matrix channels that results after processing by the transmitter and receiver portions of an SOP. The notation for this channel is $\mathbf{H}(n) \forall n$ where n is the SOP bin index. Channel identification techniques embodied herein can be applied to several preferable SOP pairs including the IFFT-FFT with cyclic prefix, the multiband filter bank, or any other of a number of well-known SOPs. The following exemplary channel identification approach exploits the correlated frequency fading across and possibly the correlated time fading in the channel. The correlation in the frequency domain arises due to the limited time delay spread of the multipath channel. The correlation in time is due to the fact that the channel, while time-varying, is driven by band-limited Doppler frequencies created by objects, which can include the transmitter and/or receiver, moving in the physical environment.

[0130] The wireless link is bidirectional, therefore each end of the link should estimate not only a receive channel, but also a transmit channel. For example, a base station should estimate both an uplink and downlink channel. In systems which employ time division duplexing (TDD), electromagnetic reciprocity implies the receive and transmit propagation environments are the same, allowing the transmit channel to be estimated from the receive channel. However, the transmit and receive electronic responses are not necessarily reciprocal, and because the net channel response includes the electronics, a calibration procedure should be used to account for these differences. This calibration procedure provides for matching in the amplitude and phase response between the multiple transmitter and receiver frequency converters. Several TDD calibration procedures are known in the prior art and will not be discussed herein.

[0131] In systems employing frequency division duplexing (FDD), the propagation medium is not reciprocal; however, the paths' angles and average strengths are the same for transmit and receive. This enables the use of subspace reciprocity, but incurs a more rigorous calibration requirement. The FDD calibration should insure subspace reciprocity

which requires that the array response vector at a given angle on receive is proportional to the corresponding vector on transmit. This requirement is satisfied by again calibrating the amplitude and phase differences among the multiple transmit and receive frequency converter channels and by matching the transmit and receive antenna element response as well as the array geometry.

[0132] An alternative approach to transmit channel estimation in FDD systems uses feedback. The transmit channel is measured by sending training symbols to the receiver, which records the amplitude induced by the training symbols. Using receiver to transmitter feedback on a separate feedback control channel, the training responses are sent back to the transmitter. The transmitter, knowing the training excitations it used and the corresponding responses through feedback, the forward channel can be estimated.

[0133] In general, channel identification can be done either with or without training. A desirable channel identification algorithm should be robust to and operate in a variety of modem implementations. A preferable MIMO channel identification technique operates with embedded training inserted into the data stream by Training Symbol Injection block 20 in each burst. In this case, both data symbols and training symbols may be transmitted within a single burst. Furthermore, the channel can be determined in one burst, or filtering training data gathered over multiple bursts. Being able to update the channel estimates after every received burst makes the overall communication system robust to time variation in the channel. In addition, frequent channel estimates reduce the destructive effects of imperfect carrier frequency recovery. Since imperfect carrier recovery imparts a phase shift to the channel that continues to grow with time, shortening the time between channel estimation events keeps the channel estimation information from becoming "stale". Note, however, any of the well known blind channel estimation techniques can be used to determine the training symbol outputs as an alternative to using training. However, adaptive blind training is more prone to generating burst errors.

[0134] The parameters to be identified are the N MIMO spatial channel matrices. Hence, there are $N \cdot M_R \cdot M_T$ complex elements to be determined,

$$H_{i,j}(n), \forall n \in [1, N], \forall i \in [1, M_R], \forall j \in [1, M_T].$$

By exploiting whatever correlation exists across the SOP bins, it may be possible to reduce the amount of overhead required to identify the channel. The amount of correlation that exists across SOP bins is determined by the specific implementation of the SOP. If the SOP implementation includes the IFFT-FFT pair, and the length of the FIR channel is time limited with $v \ll N$, then a relatively large degree of correlation exists across the SOP bins.

[0135] In certain embodiments of the invention, the desired technique should identify the MEMO channel on a burst-by-burst basis, such as those with rapidly time-varying channels. This implies that training data should be included in every burst. If the throughput of information is to be maximized, the amount of training data in each burst should be minimized. It is therefore useful to determine the minimum amount of training data required, per burst, that allows full characterization of the channel by the receiver. It turns out that the minimum number of training symbols required to sufficiently excite the MIMO channel for estimation with an OFDM SOP is $M_T v$. To understand this result, consider the identification of a SISO channel, where each of the N values of the vector $H_{i,j}$ should be found. These N values are not independent since.

$$\mathbf{H}_{i,j} = \mathbf{Y} \begin{bmatrix} \mathbf{h} \\ \mathbf{0} \end{bmatrix} = \mathbf{X} \otimes^{-1} \mathbf{Z},$$

where \mathbf{X} is a vector of all SOP bin outputs for antenna i , \mathbf{Z} is a vector of bin inputs for antenna j , and \mathbf{h} is a vector of the time-domain FIR channel from antenna j to antenna i . The matrix operator \otimes^{-1} represents element by element divide. Since the time-domain channel is time limited to v samples, only v values of the transmitted symbols, \mathbf{Z} , need to be training values. Furthermore, the identification of the SIMO channel only requires the same set of v transmitted training tones, since each SISO component in the SIMO channel is excited by the same input data. In a system embodiment with multiple inputs ($M_T > 1$), identification of the MIMO channel requires the identification of M_T separate SIMO channels. Hence, only $M_T v$ training symbols are needed to sufficiently excite the MIMO channel for channel identification.

MIMO identification

[0136] The identification of the MEMO channel is accomplished by separately exciting each of the transmit antennas that will be used for communication. This decomposes the MIMO identification problem into M_T SIMO identification problems. In order to accomplish channel identification in a single burst, M_T mutually exclusive sets of v bins are

selected from the N available bins to carry training symbols. Each transmitter antenna carries training symbols in a unique one of the M_T sets of bins, while transmitting no energy in the bins contained in the union of the remaining $M_T - 1$ sets of v bins. This is accomplished by choosing the TSWs 210A-C that correspond to training bins such that a single entry in the vector is "1" and the remaining entries equal to "0". It is the j^{th} entry of a TSW that is set equal to "1" for those training symbols which are to be transmitted from the j^{th} antenna. For example, say that symbol bin $n = 2$ is one of the training bins associated with transmit antenna 3. Then,

$$\text{TSW}(2,1) = [0 \ 0 \ 1 \ 0 \ \dots \ 0]^T, \text{ and } \text{TSW}(2,m) = 0 \text{ for } \forall m \neq 1,$$

and the corresponding training symbol $z(2,1)$. By examining the contents of each set of training bins separately, the MIMO channel response is determined by finding M_T independent SIMO channel responses.

[0137] In embodiments in which rapid updates of the channel estimate is not required, another exemplary training scheme may be employed. This training scheme involves using just one set of v training bins. On a given burst, one of the transmit antennas sends training symbols in the training bins and the other antennas transmit no energy in those bins. This allows the receiver to identify one of the M_T SIMO channels. On the next burst, a different antenna sends training symbols in the training bins while the other antennas transmit no energy in those same bins. The receiver is then able to identify another set of N SIMO channels. This procedure is repeated until training data has been sent by each of the transmit antennas, allowing the entire MIMO channel to be identified. The entire procedure is repeated continuously so that full channel is determined every M_T bursts.

SIMO channel identification

[0138] We have just shown that identification of the MIMO channel can be accomplished by successive identification of each SIMO channel. It is therefore useful to discuss specific techniques for obtaining a SIMO channel response. The following discussion assumes that the SOP is the IFFT-FFT pair. Channel identification techniques for other SOPs that exploit frequency and possibly time correlation in the similar fashion will be obvious to one skilled in the art.

[0139] It is assumed that a certain subset of available SOP bins are allocated for training. Let J be this set of frequency bins used for learning a SIMO channel. To begin, assume that J contains v bin indices. Furthermore, let Z_i be the v training symbols and $X_{t,i}$ be the received data in the training frequency-bins from antenna i . Let the quantities h_i , H_i be the estimated time-domain and frequency-domain channels from the transmit antenna under consideration to the receive antenna i . In other words, h_i is the v -length impulse response from the input under consideration to output i . Likewise, H_i is a vector of N frequency domain values for this channel. With these definitions, it can be shown that

$$\hat{h}_i = Y_{J,\bar{v}}^{-1} (X_{t,i} \otimes^{-1} Z_i), \quad (81)$$

and

$$\hat{H}_i = Y_{\bar{N},\bar{v}} \hat{h}_i, \quad (82)$$

where,

$$\bar{v} = \{1, 2, \dots, v\},$$

$$\bar{N} = \{1, 2, \dots, N\},$$

and

$$Y_{PQ} = \frac{1}{\sqrt{N}} e^{-j2\pi pq/N}, \quad \forall p \in \{P\}, \quad \forall q \in \{Q\}.$$

This also generalizes to any number of training tones, γ , in which case the set J includes γ bin indices. When $\gamma \geq v$, the

frequency domain channel can be determined by,

$$\hat{H}_i = Y_{N,v}^H (Y_{J,v}^H Y_{J,v})^{-1} Y_{J,v}^H (X_{i,l} \otimes^{-1} Z_l). \quad (83)$$

Note that many of the above calculations can be performed in advance if the training bins are predetermined and fixed. Then, the matrix $Y_{N,v}^H (Y_{J,v}^H Y_{J,v})^{-1} Y_{J,v}^H$ can be computed and stored.

[0140] Note that there is no requirement that the training symbols always reside in the same bins from burst to burst. As long as the transmitter and receiver both know where the training symbols are placed in any given burst, the training bins may be varied from one burst to the next. This may be useful to characterize the nature of colored (across SOP bins) noise and/or interference are present.

[0141] A highly advantageous simplification of (83) can be done when v training symbols are placed in bins that are evenly spaced throughout the burst. In other words, $J = \{0, \frac{N}{v}, \frac{2N}{v}, \dots, \frac{(v-1)N}{v}\}$. In this case, $Y_{J,v}^{-1}$ is equal to the v -point IFFT matrix so that equation (81) represents the execution of an v -point IFFT. One may then obtain H_i in equation (82) by performing an N -point FFT on a vector consisting of h_i padded with $N - v$ zeros. This approach to identifying H_i is only of computation order $(N + v) \log_2 v$.

Identification over multiple bursts

[0142] Identification accuracy can be improved by either increasing the number of training symbols within each burst or by averaging over multiple bursts if the channel is correlated from one burst to another. Some degree of time domain correlation exists in the channel because the Doppler frequency shifts caused by moving objects in the physical environment are band-limited. This time correlation can be exploited by recursively filtering the estimated channel from the present burst with channel estimates from previous bursts. A general filtering approach is represented by

$$\tilde{\mathbf{h}}(k+1) = \mathbf{F}(k) \tilde{\mathbf{h}}(k) + \mathbf{G}(k) \hat{\mathbf{h}}(k)$$

where $\tilde{\mathbf{h}}$ is the smoothed channel estimate of \mathbf{h} over bursts k . The particular recursive filter weights $\mathbf{F}(k)$ and $\mathbf{G}(k)$ can be derived in a number of fashions. Two exemplary filtering methods are given in the following. The first approach determines a time-invariant FIR filter for each element of \mathbf{h} based on a MMSE cost function. The second design is time-varying Kalman filter.

[0143] A particularly simple, yet effective, filter design technique is the determination of a time-invariant FIR filter, \mathbf{w} , that minimizes the MMSE between the true channel impulse response and the filtered estimate. This design approach is referred to as Wiener filtering. In this embodiment, independent fading is assumed on each element of the channel impulse response. Therefore, each element of \mathbf{h} can be considered independently. An FIR filter produces a filtered estimate by forming a weighted sum of the previous $p+1$ estimates for that particular impulse response element,

$$\tilde{h}_i(k) = \mathbf{w}^H \begin{bmatrix} \hat{h}_i(k) \\ \vdots \\ \hat{h}_i(k-p) \end{bmatrix}, \quad \forall i = 1, 2, \dots, v.$$

[0144] Using v such identical filters for each element of the impulse response, then the filtered estimate is given by $\tilde{\mathbf{h}}(k) = [\tilde{h}_1(k) \dots \tilde{h}_v(k)]^T$. The Wiener filter solution for \mathbf{w} satisfies the following equation,

$$\min_{\mathbf{w}} E \left(\left| \mathbf{w}^H \hat{\mathbf{h}}_i(k) - h_i(k) \right|^2 \right) = \min_{\mathbf{w}} E \left(\left| \mathbf{w}^H \begin{bmatrix} \hat{h}_i(k) \\ \vdots \\ \hat{h}_i(k-p) \end{bmatrix} - h_i(k) \right|^2 \right).$$

The solution for the above optimization problem is given by,

$$w = [E(h_i(k)h_i(k)^H)]^{-1} E[h_i(k)h_i(k)] = R_{n_i}^{-1} R_{n_i} h_i.$$

If each delay in the channel impulse response undergoes Raleigh fading is assumed then,

$$R_{n_i} = \sigma_h^2 \begin{bmatrix} J_0(0) & J_0(\omega(N+\nu)T) & \dots & J_0(\omega(N+\nu)T) \\ J_0(\omega(N+\nu)T) & \ddots & & \vdots \\ \vdots & & \ddots & \\ J_0(\omega(N+\nu)T) & \dots & & J_0(0) \end{bmatrix} + \sigma_e^2 \mathbb{I}$$

and

$$R_{n_i} = \sigma_h^2 \begin{bmatrix} J_0(0) \\ J_0(\omega(N+\nu)T) \\ \vdots \\ J_0(\omega(N+\nu)T) \end{bmatrix}.$$

where T is the sampling rate, ω is the maximum Doppler frequency, and J_0 is the zeroth-order Bessel function. The quantities σ_h^2 and σ_e^2 are the average channel power and the channel estimation noise power, respectively.

[0145] This filtering approach has many advantages. First, it is computationally simple. Each coefficient of the channel impulse response is filtered independently with a constant, precomputed FIR weighting. Second, the underlying time-correlation in the multipath fading channel is efficiently exploited. Third, the exact values used for the filter are optimal in a MMSE sense.

[0146] A more generalized time-varying filtering approach is now developed based on the Kalman filtering equations. A general model for the time-correlated nature of the channel impulse response is given by the following set of equations,

$$f(k+1) = Af(k) + q(k)$$

$$\tilde{h}(k) = Cf(k) + r(k)$$

where the q and r represent noises with covariances Q and R , respectively. The matrices A, C, Q, R are used to define the particular model for the correlation of the impulse response over bursts. Note that the vector \tilde{h} can also include the impulse response coefficients for more than one receive antenna. In this case, the above model can include both time correlation and correlation across space.

[0147] In a multi-access scheme, successive channel identifications may occur at an irregular rate. In this case, this Kalman filter approach is particularly useful since the filtering can be done with measurement updates and time updates,

$$\hat{f}(k+1) = A(I - L(k)C)\hat{f}(k) + AL(k)\hat{h}(k)$$

$$L(k) = \hat{P}(k)C^H(CP(k)C^H + R)^{-1}$$

$$\hat{P}(k) = A(I - L(k)C)\hat{P}(k)A^H + Q$$

$$\tilde{h}(k) = C\hat{f}(k)$$

where $L(k) = 0$ when the receiver is not receiving data in the present burst.

Interference Subspace Identification

[0148] For many of the spatial processing techniques embodied in this invention, the operation of the TSP and RSP can depend, in part, on the level of interference present in the wireless environment within which the invention operates. More specifically, it may be preferable to reduce the amount of interference contributed to other receivers by a judicious choice of the TSWs. It may also be preferable to improve the signal quality at the receiver by using RSWs that reject interference. In these cases, some quantitative measure of the interference across space and frequency is needed.

[0149] One preferable measure of the interference present is the so-called interference spatial covariance matrix, which describes interference correlation across space for each frequency bin,

$$\mathbf{R}_I(n) = E[\mathbf{x}(n)\mathbf{x}(n)^H], \quad (1)$$

where $\mathbf{x}_I(n)$ represents an M_R -length received vector of signals from the interfering transmitter(s). To be more precise, $\mathbf{R}_I(n)$ describes the interference and noise correlation across space for each frequency bin. Since we assume that the noise at the output of each receiver antenna path is additive thermal noise, and therefore that the additive noise is uncorrelated between any two antenna outputs, the noise contribution to $\mathbf{R}_I(n)$ is non-zero only on the matrix diagonal. In environments dominated by interference, i.e. the interference power at the receiver is much stronger than the additive receiver noise, the noise contribution to $\mathbf{R}_I(n)$ can be neglected. The interference covariance matrix contains information about the average spatial behavior of the interference. The eigenvectors of this matrix define the average spatial directions (in M_R -space) occupied by the interference. The eigenvalues of the matrix indicate the average power occupied by the interference in each the eigendirection. The eigendirections that are associated with large eigenvalues indicate spatial directions that receive a large amount of average interference power. The eigendirections associated with small eigenvalues indicate spatial directions that are preferable in that they receive less average interference power.

[0150] Identifying the receive covariance matrix, $\mathbf{R}_I(n)$, is required for finding preferable RSPs. An analogous transmit covariance matrix is required for finding preferable TSPs. Notice that we've defined $\mathbf{R}_I(n)$ in terms of received signal samples in Equation (1). Since the received signal samples are not usually available at the transmitter, it is preferable to derive the transmit covariance matrix from the receive covariance matrix. In time division duplex (TDD) systems, the receive and transmit covariance matrices are substantially equal when the time between reception and transmission is short relative to the rate of time variation in the channel. In frequency division duplex (FDD) systems, the transmit and receive channel values are generally not correlated with one another at any given instant in time. However, the transmit and receive covariance matrices are substantially equal in FDD systems when sufficient time averaging is used in the calculation of \mathbf{R}_I . There are many techniques for determining the interference covariance matrix, two of which are discussed below.

[0151] One interference characterization approach simply averages the received antenna signals during time periods in which the desired transceiver is not transmitting information. Since there is no desired signal arriving at the receiver, the interference (and noise) covariance is precisely equal to the measured sample covariance matrix,

$$\hat{\mathbf{R}}_I(n) = \hat{\mathbf{R}}_x(n) = \frac{1}{k_2 - k_1 + 1} \sum_{j=k_1}^{k_2} \mathbf{x}(n, j)\mathbf{x}(n, j)^H.$$

In TDD systems, one can make use of "dead-time" to collect samples from the receiver during which time no energy from the transmitting end arrives at the receiver. The "dead-time" is approximately equal to the round trip propagation delay between the two ends of the wireless communications link, and occurs when a transceiver switches from transmission mode to reception mode. In the above equation, k_1 and k_2 are the burst indexes corresponding to the first and last bursts received during the dead time. Thus, the interference covariance can be estimated with no increase in overhead.

[0152] The interference covariance matrices can also be determined while the desired signal is being transmitted to the receiver. One approach involves first determining the interference signal and subsequently finding the interference signal covariance. The estimated received interference is formed by subtracting the estimated desired signal from the total received signal,

$$\hat{\mathbf{i}}(n, k) = \mathbf{x}(n, k) - \hat{\mathbf{H}}(n, k)\hat{\mathbf{z}}(n, k).$$

Therefore, once the channel is identified and the information symbols determined, the remaining signal is considered to be interference. The interference covariance matrix for bin n , averaged over K bursts is given by,

$$\mathbb{R}_I(n, k) = \frac{1}{K} \sum_{j=k-K+1}^k \hat{\mathbb{I}}(n, k) \hat{\mathbb{I}}(n, k)^H.$$

[0153] It is understood that when estimating the covariance matrix, it may be desirable to filter the covariance matrix estimates. It may also be advantageous in certain embodiments to determine an average interference covariance matrix across SOP bins. For example, within a multiple access system bursts may only be received occasionally, making it difficult to acquire a sufficient number of bursts with which to form an accurate covariance matrix for each bin. So instead of averaging over time (a series of received bursts), a covariance matrix is formed by averaging over the SOP bins of a single burst,

$$\mathbb{R}_I(k) = \frac{1}{N} \sum_{n=1}^N \hat{\mathbb{I}}(n, k) \hat{\mathbb{I}}(n, k)^H.$$

[0154] It may also be preferable to estimate the interference covariance matrices in an alternate frequency band. This can be done using the "dead-time" approach given above. This may be advantageous when the transceiver has the capability of choosing alternate frequency bands for communicating. Estimates of interference in alternate bands provides the foundation for an adaptive frequency hopped scheme.

[0155] It is understood that the examples and embodiments described herein are for illustrative purposes only and that various modifications or changes in light thereof will be suggested to persons skilled in the art. For example, much of the above discussion concerns signal processing in the context of a wireless communication system where multiple inputs or multiple outputs are accessed by multiple transmitter antenna elements or multiple receiver antenna elements. However, the present invention is also useful in the context of wireline channels accessible via multiple inputs or multiple outputs.

Claims

1. A method for transmitting information via a plurality of inputs to a channel in a digital communication system, the method comprising:

providing a time domain substantially orthogonalizing procedure to divide said channel into input bins;
providing one or more spatial directions for communication defined by corresponding weightings among said channel inputs wherein each input bin has at least one associated spatial direction; and
transmitting said information in subchannels by employing at least two independent parallel applications of said time domain substantially orthogonalizing procedure, the subchannels being defined by a combination of input bin and spatial direction.

2. The method of Claim 1 wherein said weightings define said one or more spatial directions so that each spatial direction corresponds to communication via exactly one channel input.
3. The method of Claim 1 wherein said weightings define said one or more spatial directions so that each spatial direction corresponds to communication via more than one channel input.
4. The method of Claim 1 wherein said weightings are chosen to minimize interference to unintended receivers.
5. The method of Claim 1 wherein said weightings are chosen based upon characterization of a desired signal subspace.
6. The method of Claim 5 wherein said weightings are chosen further based upon characterization of an undesired signal subspace.
7. The method of Claim 6 wherein said characterizations of said desired signal subspace and said undesired signal subspace are averaged over at least one of time and frequency.

8. The method of any preceding claim wherein transmitting comprises:

providing a group of input symbols wherein each input symbol corresponds to a particular input bin of said time domain substantially orthogonalizing procedure;
 5 applying ones of said weightings corresponding to each of said input bins to each of said input symbols to develop for each of said input symbols a vector of spatially processed symbols, each element of said vector corresponding to a single channel input of said plurality of channel inputs;
 applying said time domain substantially orthogonalizing procedure independently for each of said channel inputs to said spatially processed symbols; and
 10 transmitting information via said channel inputs responsive to results of said time domain substantially orthogonalizing procedure.

9. The method of any of Claims 1 to 7 wherein transmitting comprises transmitting information in subchannels defined by said input bins and at least two spatial directions associated with each of said input bins, said spatial directions
 15 being chosen independently for each of said input bins.

10. The method of Claim 9 wherein said at least two spatial directions are mutually orthogonal for each of said input bins.

11. The method of Claim 9 or 10 wherein transmitting comprises:

providing a group of input symbols wherein each input symbol corresponds to a particular input bin of said time domain substantially orthogonalizing procedure and a particular one of said at least two spatial directions;
 for each of said spatial directions applying one of said weightings to define contributions to each of said channel inputs;
 20 for each channel input, independently applying said time domain substantially orthogonalizing procedure to results of applying said weightings; and
 transmitting information via said channel inputs responsive to results of applying said time domain substantially orthogonalizing procedure.

12. The method of Claim 11 further comprising applying a coding procedure to develop said group of input symbols.

13. The method of Claim 12 wherein said coding procedure is applied independently for each of said input bins.

14. The method of Claim 12 wherein said coding procedure is applied independently for each of said spatial directions.

15. The method of Claim 14 wherein each of said spatial directions are mutually orthogonal.

16. The method of Claim 12 wherein said coding procedure is applied independently for each of said subchannels.

17. The method of any of Claims 12 to 16 wherein said coding procedure belongs to a group consisting of: convolutional coding, Reed-Solomon coding, CRC coding, block coding, trellis coding, turbo coding, and interleaving.

18. The method of Claim 9 wherein said at least two spatial directions are not mutually orthogonal for each of said input bins.

19. The method of Claim 18 wherein transmitting comprises:

coding said information to develop symbols corresponding to each of said subchannels, said coding being optimized to take advantage of multiple spatial directions;
 50 applying said time domain substantially orthogonalizing procedure independently to symbols corresponding to each of said at least two spatial directions;
 applying said weightings to results of said independent applications of said time domain substantially orthogonalizing procedure; and
 transmitting via said channel inputs responsive to results of applying said weightings.

20. The method of Claim 19 wherein said weightings are chosen to minimize interference to unintended receivers.

21. The method of Claim 19 wherein said weightings are chosen to maximize average received power.

22. The method of Claim 19 wherein coding comprises applying a multi-dimensional trellis coding procedure.
23. The method of any preceding claim wherein said time domain substantially orthogonalizing procedure belongs to one of a group consisting of an inverse Fast Fourier Transform and a Fast Fourier Transform.
24. The method of any preceding claim wherein said channel comprises a wireless channel and said plurality of channel inputs are associated with a corresponding plurality of transmitter antenna elements.
25. The method of any preceding claim further comprising: allocating bit loading and power among said plurality of subchannels.
26. A transmitter system for transmitting information via a plurality of inputs to a channel, said transmitter system comprising:
 - at least one processing element (190) that applies a time domain substantially orthogonalizing procedure to divide said channel into input bins;
a spatial processor (230) employing weightings among the channel inputs to define spatial directions wherein each input bin has at least one associated spatial direction; and
 - wherein said transmitter system transmits information in subchannels of said channel, each of said subchannels being defined by a combination of input bin and spatial direction, by employing said at least one processing element for at least two independent applications of said time domain substantially orthogonalizing procedure.
27. The transmitter system of Claim 26 wherein said weightings define said one or more spatial directions so that each spatial direction corresponds to communication via more than one channel input.
28. The transmitter system of Claim 26 wherein said weightings are chosen to minimize interference to unintended receivers.
29. The transmitter system of Claim 26 wherein said weightings are chosen based upon characterization of a desired signal subspace.
30. The transmitter of Claim 29 wherein said weightings are chosen further based upon characterization of an undesired signal subspace.
31. The transmitter system of Claim 30 wherein said characterizations of said desired signal subspace and said undesired signal subspace are averaged over at least one of time and frequency.
32. The transmitter system of Claim 26 further comprising:
 - a system input that receives a group of input symbols wherein each input symbol corresponds to a particular input bin of said time domain substantially orthogonalizing procedure; and wherein said spatial processor applies ones of said weightings corresponding to each of said input bins to each of said input symbols to develop for each of said input symbols a vector of spatially processed symbols, each element of said vector corresponding to a single channel input of said plurality of channel inputs; and wherein said at least one processing element applies said time domain substantially orthogonalizing procedure independently for each of said channel inputs to said spatially processed symbols; and wherein said transmitter system transmits via said channel inputs responsive to results of said time domain substantially orthogonalizing procedure.
33. The transmitter system of Claim 26 wherein information is transmitted in subchannels defined by said input bins and at least two spatial directions associated with each of said input bins, said spatial directions being chosen independently for each of said input bins.
34. The transmitter system of Claim 33 wherein said at least two spatial directions are mutually orthogonal for each of said input bins.
35. The transmitter system of Claim 33 or 34 further comprising:

a system input that receives a group of input symbols wherein each input symbol corresponds to a particular input bin of said time domain substantially orthogonalizing procedure and a particular one of said at least two spatial directions; and wherein

said spatial processor, for each of said spatial directions, applies one of said weightings to define contributions to each of said channel inputs; and wherein

said at least one processing element independently applies said time domain substantially orthogonalizing procedure to results of applying said weightings; and wherein

said transmitter system transmits via said channel inputs responsive to results of applying said time domain substantially orthogonalizing procedure.

36. The transmitter system of Claim 35 wherein said weightings are selected according to singular value decompositions of matrices **characterizing** communication via each input bin of said channel.

37. The transmitter system of Claim 35 or 36 further comprising an encoding system that applies a coding procedure to develop said group of input symbols.

38. The transmitter system of Claim 37 wherein said coding procedure is applied independently for each of said input bins.

39. The transmitter system of Claim 37 wherein said coding procedure is applied independently for each of said spatial directions.

40. The transmitter system of Claim 39 wherein each of said spatial directions are mutually orthogonal.

41. The transmitter system of Claim 37 wherein said coding procedure is applied independently for each of said subchannels.

42. The transmitter system of any of Claims 37 to 41 wherein said coding procedure belongs to a group consisting of: convolutional coding, Reed-Solomon coding, CRC coding, block coding, trellis coding, turbo coding, and interleaving.

43. The transmitter system of Claim 33 wherein said at least two spatial directions are not mutually orthogonal for each of said input bins.

44. The transmitter system of Claim 43 further comprising:

an encoding system that encodes said information to develop symbols corresponding to each of said subchannels, said coding being optimized to take advantage of multiple spatial directions; and wherein said at least one processing element applies said time domain substantially orthogonalizing procedure independently to symbols corresponding to each of said at least two spatial directions; and wherein said spatial processor applies said weightings to results of said independent applications of said time domain substantially orthogonalizing procedure; and wherein said transmitter system transmits via said plurality of channel inputs responsive of results of applying said weightings.

45. The transmitter system of Claim 44 wherein said weightings are selected so that there is a one to one association between channel inputs and spatial directions.

46. The transmitter system of Claim 44 wherein said weightings are chosen to minimize interference to unintended receivers.

47. The transmitter system of Claim 44 wherein said weightings are chosen to maximize average received power.

48. The transmitter system of Claim 44 wherein said encoding system applies a multi-dimensional trellis coding procedure.

49. The transmitter system of any of Claims 26 to 48 wherein said time domain substantially orthogonalizing procedure belongs to one of a group consisting of an inverse Fast Fourier Transform and a Fast Fourier Transform.

50. The transmitter system of any of Claims 26 to 49 wherein said channel comprises a wireless channel and said plurality of channel inputs are associated with a corresponding plurality of transmitter antenna elements.

51. The transmitter system of any of Claims 26 to 50 further comprising:

a bit loading system that allocates bit loading and power among said plurality of subchannels.

52. A method for receiving information via a plurality of outputs from a channel in a digital communication system, said method comprising:

providing a time domain substantially orthogonalizing procedure to divide said channel into output bins; providing one or more spatial directions for communication defined by corresponding weightings among said channel outputs wherein each output bin has at least one associated spatial direction; and receiving information via subchannels of said channel by employing at least two independent parallel applications of said time domain substantially orthogonalizing procedure, each subchannel being defined by a combination of output bin and spatial direction.

53. The method of Claim 52 wherein said weightings define said one or more spatial directions so that each spatial direction corresponds to communication via exactly one channel output.

54. The method of Claim 52 wherein said weightings define said one or more spatial directions so that each spatial direction corresponds to communication via more than one channel output.

55. The method of Claim 52 wherein said weightings are chosen to minimize interference from undesired transmitters.

56. The method of Claim 52 wherein said weightings are chosen based upon characterization of a desired signal subspace.

57. the method of Claim 56 wherein said weightings are chosen further based upon characterization of an undesired signal subspace.

58. The method of Claim 57 wherein said characterizations of said desired signal subspace and said undesired signal subspace are averaged over at least one of time and frequency.

59. The method of any of Claims 52 to 58 wherein receiving comprises:

receiving input time domain symbols via said channel outputs; applying said substantially orthogonalizing procedure to said input time domain symbols independently for each of said channel outputs; and applying ones of said weightings corresponding to each of said output bins to results of said substantially orthogonalizing procedure to obtain symbols transmitted via each of said subchannels.

60. The method of Claim 52 wherein receiving comprises receiving information in subchannels defined by said output bins and at least two spatial directions associated with each of said output bins, said spatial directions being chosen independently for each of said output bins.

61. The method of Claim 60 wherein said at least two spatial directions are mutually orthogonal for each of said output bins.

62. The method of Claim 60 or 61 wherein receiving comprises:

receiving time domain symbols via said channel outputs; for each of said channel outputs, independently applying said time domain substantially orthogonalizing procedure to said received input time domain symbols; and applying said weightings to results of said time domain substantially orthogonalizing procedure to obtain symbols transmitted via each of said subchannels.

63. The method of Claim 62 further comprising applying a decoding procedure to said symbols transmitted via each

of said subchannels.

64. The method of Claim 63 wherein said decoding procedure is applied independently for each of said output bins.

5 65. The method of Claim 63 wherein said decoding procedure is applied independently for each of said spatial directions.

66. The method of Claim 65 wherein each of said spatial directions are mutually orthogonal.

10 67. The method of Claim 63 wherein said decoding procedure is applied independently for each of said subchannels.

68. The method of Claim 63 wherein said decoding procedure is based on one of: convolutional coding, Reed-Solomon coding, CRC coding, block coding, trellis coding, turbo coding, and interleaving.

15 69. The method of Claim 60 wherein said at least two spatial directions are not mutually orthogonal for each of said output bins.

70. The method of Claim 69 wherein receiving comprises:

20 receiving time domain symbols via said channel outputs;
for each of said channel outputs, applying said weightings to said time domain symbols to obtain results corresponding to each of said spatial directions;
applying said time domain substantially orthogonalizing procedure to said results independently for each of
said spatial directions to obtain symbols transmitted via each of said subchannels; and
25 decoding said symbols transmitted via each of said subchannels according to a coding scheme optimized to take advantage of multiple spatial directions.

71. The method of Claim 70 wherein said weightings are chosen to minimize interference from undesired transmitters.

30 72. The method of Claim 70 wherein said weightings are chosen to maximize average received power.

73. The method of Claim 70 wherein said coding scheme comprises a multi-dimensional trellis coding procedure.

35 74. The method of any of Claims 52 to 73 wherein said time domain substantially orthogonalizing procedure belongs to one of a group consisting of a Fast Fourier Transform and an inverse Fast Fourier Transform.

75. The method of any of Claims 52 to 73 wherein said time domain substantially orthogonalizing procedure belongs to one of a group consisting of a discrete cosine transform, a Hilbert transform, a wavelet transform, and processing through a plurality of frequency converter/bandpass filter pairs centered at spaced apart frequencies.

40 76. The method of any of Claims 52 to 75 wherein said channel comprises a wireless channel and said plurality of channel outputs are associated with a corresponding plurality of receiver antenna elements.

77. The method of any of Claims 52 to 76 further comprising:

45 receiving via a particular one of said channel outputs, at least v frequency domain training symbols transmitted via a particular input to said channel, v being an extent in symbol periods of a duration of significant terms of an impulse response of channel component coupling said particular channel input and said particular channel output;
50 applying said time domain substantially orthogonalizing procedure to said at least v received training symbols to obtain a time domain response for said channel component; and
applying an inverse of said substantially orthogonalizing procedure to a zero-padded version of said time domain response to obtain a frequency response for said channel component.

55 78. A receiver system for receiving information via a plurality of outputs from a channel, said receiver system comprising:

at least one processing element (200) that applies a time domain substantially orthogonalizing procedure to

divide said channel into output bins;
a spatial processor (210) employing weightings among said channel outputs to define spatial directions wherein each output bin has at least one associated spatial direction; and

5 wherein said receiver system receives information via subchannels of said channel, by employing at least two independent parallel applications of said substantially orthogonalizing procedure by said at least one processing element, each of said subchannels being defined by a combination of output bin and spatial direction.

79. The receiver system of Claim 78 wherein said weightings are chosen to minimize interference from undesired transmitters.

80. The receiver system of Claim 78 wherein said weightings are chosen based upon characterization of a desired signal subspace.

81. The receiver system of Claim 80 wherein said weightings are chosen further based upon characterization of an undesired signal subspace.

82. The receiver system of Claim 81 wherein said characterizations of said desired signal subspace and said undesired signal subspace are averaged over at least one of time and frequency.

83. The receiver system of Claim 78 further comprising:

a system input that receives input time domain symbols via said channel outputs; and wherein said at least one processing element applies said substantially orthogonalizing procedure to said time domain input symbols independently for each of said channel outputs; and wherein said spatial processor applies ones of said weightings corresponding to each of said output bins to results of said substantially orthogonalizing procedure to obtain symbols transmitted via each of said subchannels.

84. The receiver system of Claim 78 wherein said receiver system receives information in subchannels defined by said output bins and at least two spatial directions associated with each of said output bins, each of said output bins having identical associated spatial directions.

85. The receiver system of Claim 84 further comprising:

a system input that receives input time domain symbols via said channel outputs; and wherein said spatial processor, for each of said channel outputs, applies a corresponding one of said weightings to said received input time domain symbols, each of said weightings being associated with a particular one of said at least two spatial directions; and wherein said at least one processing element, for each of said at least two spatial directions, independently applies said time domain substantially orthogonalizing procedure to results of applying said weightings to obtain symbols transmitted via each of said subchannels.

86. The receiver system of Claim 78 wherein said receiver system receives information in subchannels defined by said output bins and at least two spatial directions associated with each of said output bins, said spatial directions being chosen independently for each of said output bins.

87. The receiver system of Claim 86 wherein said at least two spatial directions are mutually orthogonal for each of said output bins.

88. The receiver system of Claim 86 or 87 further comprising:

a system input that receives time domain symbols via said channel outputs; and wherein said at least one processing element, for each of said channel outputs, independently applies said time domain substantially orthogonalizing procedure to said received input time domain symbols; and wherein said spatial processor applies said weightings to results of said time domain substantially orthogonalizing procedure to obtain symbols transmitted via each of said subchannels.

89. The receiver system of Claim 88 wherein said weightings are selected according to singular value decompositions

of matrices **characterizing** communication via each output bin of said channel.

5 90. The receiver system of Claim 88 or 89 further comprising a decoding system that applies a decoding procedure to said symbols transmitted via each of said subchannels.

91. The receiver system of Claim 90 wherein said decoding procedure is applied independently for each of said output bins.

10 92. The receiver system of Claim 90 wherein said decoding procedure is applied independently for reach of said spatial directions.

93. The receiver system of Claim 92 wherein each of said spatial directions are mutually orthogonal.

15 94. The receiver system of Claim 90 wherein said decoding procedure is applied independently for each of said subchannels.

95. The receiver system of Claim 90 wherein said decoding procedure is based on one of: convolutional coding, Reed-Solomon coding, CRC coding, block coding, trellis coding, turbo coding, and interleaving.

20 96. The receiver system of Claim 86 wherein said at least two spatial directions are not mutually orthogonal for each of said output bins.

97. The receiver system of Claim 96 further comprising:

25 a system input that receives time domain symbols via said channel outputs; and wherein said spatial processor, for each of said channel outputs, applies said weightings to said time domain symbols to obtain results symbols corresponding to each of said spatial directions; and wherein said at least one processing element applies said time domain substantially orthogonalizing procedure to said result symbols independently for each of said spatial directions to obtain symbols transmitted via each of said subchannels; and wherein said receiver system further comprises;
30 a decoding system that decodes symbols transmitted via each of said subchannels according to a coding scheme optimized to take advantage of multiple spatial directions.

35 98. The receiver system of Claim 97 wherein said weightings are chosen to minimize interference from undesired transmitters.

99. The receiver system of Claim 97 wherein said weightings are chosen to maximize average received power.

40 100. The receiver system of Claim 97 wherein said coding scheme comprises a multi-dimensional trellis coding procedure.

101. The receiver system of any of Claims 78 to 100 wherein said time domain substantially orthogonalizing procedure belongs to one of a group consisting of a Fast Fourier Transform and an inverse Fast Fourier Transform.

45 102. The receiver system of Claims 78 to 101 wherein said channel comprises a wireless channel and said plurality of channel outputs are associated with a corresponding plurality of receiver antenna elements.

103. A transmitter system for transmitting information via a plurality of inputs to a channel, said transmitter system comprising:

50 at least one processing element (190) that performs a time domain substantially orthogonalizing procedure to divide said channel into input bins; an encoding system (10) that applies an encoding scheme to information, said encoding scheme advantageously distributing information among multiple spatial directions; and

55 wherein said transmitter system transmits information as encoded by said encoding system in subchannels of said channel, each of said subchannels being defined by a combination of input bin and spatial direction.

104. The transmitter system of Claim 103 wherein said encoding scheme comprises a multi-dimensional trellis coding

scheme.

105. The transmitter system of Claim 103 or 104 wherein each of said multiple spatial directions corresponds to transmission via a single channel input.

106. The transmitter system of Claim 103 or 104 wherein each said multiple spatial directions corresponds to a weighting among said channel inputs.

107. The transmitter system of Claim 106 wherein said weighting is applied to a time domain signal.

108. The transmitter system of any of Claims 103 to 107 wherein said encoding scheme codes across input bins.

109. A receiver system for receiving information via a plurality of outputs from a channel, the receiver system comprising:

at least one processing element (200) that performs a time domain substantially orthogonalizing procedure to divide said channel into output bins;
a decoding system (150) that removes an encoding scheme from received information, said encoding scheme advantageously distributing information among multiple spatial directions; and

wherein said receiver system receives said information in subchannels of said channel, each of said subchannels being defined by a combination of output bin and spatial direction.

110. The receiver system of Claim 109 wherein said encoding scheme comprises a multi-dimensional trellis coding scheme.

111. The receiver system of Claim 109 or 110 wherein each of said multiple spatial directions corresponds to reception via a single channel output.

112. The receiver system of Claim 109 or 110 wherein each of said multiple spatial directions corresponds to a weighting among said channel outputs.

113. The receiver system of Claim 112 wherein said weighting is applied to a time domain signal.

114. The receiver system of any of Claims 109 to 113 wherein said encoding scheme codes across output bins.

Patentansprüche

1. Verfahren zum Senden von Informationen über mehrere Eingänge zu einem Kanal in einem digitalen Kommunikationssystem, wobei das Verfahren umfasst:

Vorsehen einer den Zeitbereich im Wesentlichen orthogonalisierenden Prozedur, um den Kanal in Eingangs-Bins zu unterteilen;

Vorsehen einer oder mehrerer räumlicher Richtungen für die Kommunikation, die durch entsprechende Gewichtungen unter den Kanaleingängen definiert sind, wobei jedem Eingangs-Bin wenigstens eine räumliche Richtung zugeordnet ist; und

Senden der Informationen in Unterkanälen unter Verwendung wenigstens zweier unabhängiger paralleler Anwendungen der den Zeitbereich im Wesentlichen orthogonalisierenden Prozedur, wobei die Unterkanäle durch eine Kombination aus Eingangs-Bin und räumlicher Richtung definiert sind.

2. Verfahren nach Anspruch 1, bei dem die Gewichtungen die eine oder die mehreren räumlichen Richtungen so definieren, dass jede räumliche Richtung einer Kommunikation über genau einen Kanaleingang entspricht.

3. Verfahren nach Anspruch 1, bei dem die Gewichtungen die eine oder die mehreren räumlichen Richtungen so definieren, dass jede räumliche Richtung einer Kommunikation über mehr als einen Kanaleingang entspricht.

4. Verfahren nach Anspruch 1, bei dem die Gewichtungen so gewählt sind, dass die Störung für nicht gewünschte Empfänger minimiert wird.

5. Verfahren nach Anspruch 1, bei dem die Gewichtungen auf der Grundlage der Charakterisierung eines gewünschten Signaluntertraums gewählt werden.
- 5 6. Verfahren nach Anspruch 5, bei dem die Gewichtungen ferner auf der Grundlage der Charakterisierung eines nicht gewünschten Signaluntertraums gewählt werden.
7. Verfahren nach Anspruch 6, bei dem die Charakterisierungen des gewünschten Signaluntertraums und des nicht gewünschten Signaluntertraums über die Zeit und/oder die Frequenz gemittelt werden.
- 10 8. Verfahren nach einem vorhergehenden Anspruch, bei dem das Senden umfasst:

Vorsehen einer Gruppe von Eingangssymbolen, wobei jedes Eingangssymbol einem bestimmten Eingangs-Bin der den Zeitbereich im Wesentlichen orthogonalisierenden Prozedur entspricht;
Eingeben von Gewichtungen, die jedem der Eingangs-Bins entsprechen, in jedes der Eingangssymbole, um
15 für jedes der Eingangssymbole einen Vektor aus räumlich verarbeiteten Symbolen zu entwickeln, wobei jedes Element des Vektors einem einzigen Kanaleingang der mehreren Kanäleingänge entspricht;
Anwenden der den Zeitbereich im Wesentlichen orthogonalisierenden Prozedur unabhängig für jeden der Kanäleingänge auf die räumlich verarbeiteten Symbole; und
Senden von Informationen über die Kanäleingänge in Reaktion auf Ergebnisse der den Zeitbereich im Wesentlichen orthogonalisierenden Prozedur.
20
9. Verfahren nach einem der Ansprüche 1 bis 7, bei dem das Senden das Senden von Informationen in Unterkanälen umfasst, die durch die Eingangs-Bins und wenigstens zwei räumliche Richtungen, die jedem der Eingangs-Bins zugeordnet sind, definiert sind, wobei die räumlichen Richtungen unabhängig für jedes der Eingangs-Bins gewählt werden.
25
10. Verfahren nach Anspruch 9, bei dem die wenigstens zwei räumlichen Richtungen für jedes der Eingangs-Bins zueinander orthogonal sind.
- 30 11. Verfahren nach Anspruch 9 oder 10, bei dem das Senden umfasst:

Vorsehen einer Gruppe von Eingangssymbolen, wobei jedes Eingangssymbol einem bestimmten Eingangs-Bin der den Zeitbereich im Wesentlichen orthogonalisierenden Prozedur und einer bestimmten der wenigstens zwei räumlichen Richtungen entspricht;
35 Anwenden einer der Gewichtungen auf jede der räumlichen Richtungen, um Beiträge zu jedem der Kanäleingänge zu definieren;
Anwenden der den Zeitbereich im Wesentlichen orthogonalisierenden Prozedur unabhängig für jeden Kanaleingang auf Ergebnisse der Anwendung der Gewichtungen; und
Senden von Informationen über die Kanäleingänge in Reaktion auf Ergebnisse der Anwendung der den Zeitbereich im Wesentlichen orthogonalisierenden Prozedur.
40
12. Verfahren nach Anspruch 11, das ferner das Anwenden einer Codierungsprozedur umfasst, um die Gruppe von Eingangssymbolen zu entwickeln.
- 45 13. Verfahren nach Anspruch 12, bei dem die Codierungsprozedur unabhängig für jedes der Eingangs-Bins angewendet wird.
14. Verfahren nach Anspruch 12, bei dem die Codierungsprozedur unabhängig für jede der räumlichen Richtungen angewendet wird.
50
15. Verfahren nach Anspruch 14, bei dem die räumlichen Richtungen zueinander orthogonal sind.
16. Verfahren nach Anspruch 12, bei dem die Codierungsprozedur unabhängig für jeden der Unterkanäle angewendet wird.
55
17. Verfahren nach einem der Ansprüche 12 bis 16, bei dem die Codierungsprozedur zu einer Gruppe gehört, die besteht aus: einer Faltungscodierung, einer Reed-Solomon-Codierung, einer CRC-Codierung, einer Blockcodierung, einer Trellis-Codierung, einer Turbocodierung und einer Verschachtelung.

18. Verfahren nach Anspruch 9, bei dem die wenigstens zwei räumlichen Richtungen nicht für jedes der Eingangs-Bins zueinander orthogonal sind.

19. Verfahren nach Anspruch 18, bei dem das Senden umfasst:

Codieren der Informationen, um Symbole zu entwickeln, die jedem der Unterkanäle entsprechen, wobei die Codierung so optimiert ist, dass der Vorteil mehrerer räumlicher Richtungen genutzt wird;

Anwenden der den Zeitbereich im Wesentlichen orthogonalisierenden Prozedur unabhängig auf Symbole, die jeder der wenigstens zwei räumlichen Richtungen entsprechen;

Anwenden der Gewichtungen auf Ergebnisse der unabhängigen Anwendungen der den Zeitbereich im Wesentlichen orthogonalisierenden Prozedur; und

Senden über die Kanaleingänge in Reaktion auf Ergebnisse des Anwendens der Gewichtungen.

20. Verfahren nach Anspruch 19, bei dem die Gewichtungen so gewählt sind, dass die Störung für nicht gewünschte Empfänger minimiert sind,

21. Verfahren nach Anspruch 19, bei dem die Gewichtungen so gewählt sind, dass die durchschnittlich empfangene Leistung maximiert wird.

22. Verfahren nach Anspruch 19, bei dem die Codierung das Anwenden einer mehrdimensionalen Trellis-Codierungs-prozedur umfasst.

23. Verfahren nach einem vorhergehenden Anspruch, bei dem die den Zeitbereich im Wesentlichen orthogonalisierende Prozedur zu einer Gruppe gehört, die aus einer inversen schnellen Fourier-Transformation und aus einer schnellen Fourier-Transformation besteht.

24. Verfahren nach einem vorhergehenden Anspruch, bei dem der Kanal einen drahtlosen Kanal umfasst und die mehreren Kanaleingänge einer entsprechenden Mehrzahl von Sendeantennenelementen zugeordnet sind.

25. Verfahren nach einem vorhergehenden Anspruch, das ferner umfasst: Zuweisen von Bitladen und Leistung an die mehreren Unterkanäle.

26. Sendersystem zum Senden von Informationen über mehrere Eingänge zu einem Kanal, wobei das Sendersystem umfasst:

wenigstens ein Verarbeitungselement (190), das eine den Zeitbereich im Wesentlichen orthogonalisierende Prozedur anwendet, um die Kanäle in Eingangs-Bins zu unter-teilen;

einen räumlichen Prozessor (230), der Gewichtungen für die Kanaleingänge bzw. unter den Kanaleingängen verwendet, um räumliche Richtungen zu definieren, wobei jedes Eingangs-Bin wenigstens eine zugeordnete räumliche Richtung besitzt; und

wobei das Sendersystem Informationen in Unterkanälen des Kanals sendet, wobei jeder der Unterkanäle durch eine Kombination aus Eingangs-Bin und räumlicher Richtung definiert ist, indem das wenigstens eine Verarbeitungselement für wenigstens zwei unabhängige Anwendungen der den Zeitbereich im Wesentlichen orthogonalisierenden Prozedur verwendet wird.

27. Sendersystem nach Anspruch 26, bei dem die Gewichtungen die eine oder die mehreren räumlichen Richtungen so definieren, dass jede räumliche Richtung einer Kommunikation über mehr als einen Kanaleingang entspricht.

28. Sendersystem nach Anspruch 26, bei dem die Gewichtungen so gewählt sind, dass die Störung für nicht gewünschte Empfänger minimiert wird.

29. Sendersystem nach Anspruch 26, bei dem die Gewichtungen auf der Grundlage der Charakterisierung eines gewünschten Signalunterraums gewählt sind.

30. Sendersystem nach Anspruch 29, bei dem die Gewichtungen ferner auf der Grundlage der Charakterisierung eines nicht gewünschten Signalunterraums gewählt sind.

31. Sendersystem nach Anspruch 30, bei dem die Charakterisierungen des gewünschten Signalunterraums und des nicht gewünschten Signalunterraums über die Zeit und/oder die Frequenz gemittelt werden.

32. Sendersystem nach Anspruch 26, das ferner umfasst:

einen Systemeingang, der eine Gruppe von Eingangssymbolen empfängt, wobei jedes Eingangssymbol einem bestimmten Eingangs-Bin der den Zeitbereich im Wesentlichen orthogonalisierenden Prozedur entspricht; und bei dem der räumliche Prozessor einige der Gewichtungen, die jedem der Eingangs-Bins entsprechen, auf die Eingangssymbole anwendet, um für jedes der Eingangssymbole einen Vektor aus räumlich verarbeiteten Symbolen zu entwickeln, wobei jedes Element des Vektors einem einzigen Kanaleingang der mehreren Kanaleingänge entspricht; und bei dem das wenigstens eine Verarbeitungselement die den Zeitbereich im Wesentlichen orthogonalisierende Prozedur unabhängig für jeden der Kanaleingänge auf die räumlich verarbeiteten Symbole anwendet; und bei dem das Sendersystem in Reaktion auf Ergebnisse der den Zeitbereich im Wesentlichen orthogonalisierenden Prozedur über die Kanaleingänge sendet

33. Sendersystem nach Anspruch 26, bei dem Informationen in Unterkanälen gesendet werden, die durch die Eingangs-Bins und wenigstens zwei räumliche Richtungen, die jedem der Eingangs-Bins zugeordnet sind, definiert sind, wobei die räumlichen Richtungen unabhängig für jedes der Eingangs-Bins gewählt sind.

34. Sendersystem nach Anspruch 33, bei dem die wenigstens zwei räumlichen Richtungen für jedes der Eingangs-Bins zueinander orthogonal sind.

35. Sendersystem nach Anspruch 33 oder 34, das ferner umfasst:

einen Systemeingang, der eine Gruppe von Eingangssymbolen empfängt, wobei jedes Eingangssymbol einem bestimmten Eingangs-Bin der den Zeitbereich im Wesentlichen orthogonalisierenden Prozedur und einer bestimmten der wenigstens zwei räumlichen Richtungen entspricht; und bei dem der räumliche Prozessor für jede der räumlichen Richtungen eine der Gewichtungen anwendet, um Beiträge zu jedem der Kanaleingänge zu definieren; und bei dem das wenigstens eine Verarbeitungselement die den Zeitbereich im Wesentlichen orthogonalisierende Prozedur unabhängig auf Ergebnisse der Anwendung der Gewichtungen anwendet; und bei dem das Sendersystem in Reaktion auf Ergebnisse der Anwendung der den Zeitbereich im Wesentlichen orthogonalisierenden Prozedur über die Kanaleingänge sendet.

36. Sendersystem nach Anspruch 35, bei dem die Gewichtungen in Übereinstimmung mit Zerlegungen singulärer Werte von Matrizen, die die Kommunikation über jedes Eingangs-Bin des Kanals charakterisieren, ausgewählt werden.

37. Sendersystem nach Anspruch 35 oder 36, das ferner ein Codierungssystem umfasst, das eine Codierungsprozedur anwendet, um die Gruppe von Eingangssymbolen zu entwickeln.

38. Sendersystem nach Anspruch 37, bei dem die Codierungsprozedur unabhängig für jedes Eingangs-Bin angewendet wird.

39. Sendersystem nach Anspruch 37, bei dem die Codierungsprozedur unabhängig für jede der räumlichen Richtungen angewendet wird.

40. Sendersystem nach Anspruch 39, bei dem alle räumlichen Richtungen zueinander orthogonal sind.

41. Sendersystem nach Anspruch 37, bei dem die Codierungsprozedur unabhängig für jeden der Unterkanäle angewendet wird.

42. Sendersystem nach einem der Ansprüche 37 bis 41, bei dem die Codierungsprozedur zu einer Gruppe gehört, die besteht aus: einer Faltungscodierung, einer Reed-Solomon-Codierung, einer CRC-Codierung, einer Blockcodierung, einer Trellis-Codierung, einer Thrbocodierung und einer Verschachtelung.

43. Sendersystem nach Anspruch 33, bei dem die wenigstens zwei räumlichen Richtungen nicht für jedes der Ein-

gangs-Bins zueinander orthogonal sind.

44. Sendersystem nach Anspruch 43, das ferner umfasst:

ein Codierungssystem, das die Informationen codiert, um Symbole zu entwickeln, die jedem der Unterkanäle entsprechen, wobei die Codierung so optimiert ist, dass der Vorteil mehrerer räumlicher Richtungen genutzt wird; und bei dem das wenigstens eine Verarbeitungselement die den Zeitbereich im Wesentlichen orthogonalisierende Prozedur unabhängig auf Symbole anwendet, die jeder der wenigstens zwei räumlichen Richtungen entsprechen; und bei dem der räumliche Prozessor die Gewichtungen auf Ergebnisse der unabhängigen Anwendungen der den Zeitbereich im Wesentlichen orthogonalisierenden Prozedur anwendet; und bei dem das Sendersystem in Reaktion auf Ergebnisse der Anwendung der Gewichtungen über die mehreren Kanaleingänge sendet.

45. Sendersystem nach Anspruch 44, bei dem die Gewichtungen so gewählt sind, dass zwischen den Kanaleingängen und den räumlichen Richtungen eine Eins-zu-Eins-Zuordnung besteht.

46. Sendersystem nach Anspruch 44, bei dem die Gewichtungen so gewählt sind, dass die Störung für nicht gewünschte Empfänger minimiert ist.

47. Sendersystem nach Anspruch 44, bei dem die Gewichtungen so gewählt sind, dass die durchschnittlich empfangene Leistung maximiert ist.

48. Sendersystem nach Anspruch 44, bei dem das Codierungssystem eine mehrdimensionale Trellis-Codierungsprozedur anwendet.

49. Sendersystem nach einem der Ansprüche 26 bis 48, bei dem die den Zeitbereich im Wesentlichen orthogonalisierende Prozedur zu einer Gruppe gehört, die aus einer inversen schnellen Fourier-Transformation und aus einer schnellen Fourier-Transformation besteht.

50. Sendersystem nach einem der Ansprüche 26 bis 49, bei dem der Kanal einen drahtlosen Kanal umfasst und die mehreren Kanaleingänge einer entsprechenden Mehrzahl von Senderantennenelementen zugeordnet sind.

51. Sendersystem nach einem der Ansprüche 26 bis 50, das ferner umfasst:

ein Bitladesystem, das den mehreren Unterkanälen ein Bitladen und Leistung zuweist.

52. Verfahren zum Empfangen von Informationen über mehrere Ausgänge von einem Kanal in einem digitalen Kommunikationssystem, wobei das Verfahren umfasst:

Vorsehen einer den Zeitbereich im Wesentlichen orthogonalisierenden Prozedur, um den Kanal in Ausgangs-Bins zu unterteilen;

Vorsehen einer oder mehrerer räumlicher Richtungen für die Kommunikation, die durch entsprechende Gewichte unter den Kanalausgängen definiert sind, wobei jedem Ausgangs-Bin wenigstens eine räumliche Richtung zugeordnet ist; und

Empfangen von Informationen über Unterkanäle des Kanals durch Verwenden wenigstens zweier unabhängiger paralleler Anwendungen der den Zeitbereich im Wesentlichen orthogonalisierenden Prozedur, wobei jeder Unterkanal durch eine Kombination aus Ausgangs-Bin und räumlicher Richtung definiert ist.

53. Verfahren nach Anspruch 52, bei dem die Gewichtungen die eine oder die mehreren räumlichen Richtungen definieren, so dass jede räumliche Richtung einer Kommunikation über genau einen Kanalausgang entspricht.

54. Verfahren nach Anspruch 52, bei dem die Gewichtungen die eine oder die mehreren räumlichen Richtungen definieren, so dass jede räumliche Richtung einer Kommunikation über mehr als einen Kanalausgang entspricht.

55. Verfahren nach Anspruch 52, bei dem die Gewichtungen so gewählt sind, dass die Störung von nicht gewünschten Sendern minimiert wird.

56. Verfahren nach Anspruch 52, bei dem die Gewichtungen auf der Grundlage einer Charakterisierung eines gewünschten Signalunterraums gewählt werden.
57. Verfahren nach Anspruch 56, bei dem die Gewichtungen ferner auf der Grundlage einer Charakterisierung eines nicht gewünschten Signalunterraums gewählt werden.
58. Verfahren nach Anspruch 57, bei dem die Charakterisierungen des gewünschten Signalunterraums und des nicht gewünschten Signalunterraums über die Zeit und/oder die Frequenz gemittelt werden.
59. Verfahren nach einem der Ansprüche 52 bis 58, bei dem das Empfangen umfasst:
- Empfangen von Eingangszeitbereichssymbolen über die Kanalausgänge;
Anwenden der im Wesentlichen orthogonalisierenden Prozedur auf die Eingangszeitbereichssymbole unabhängig für jeden der Kanalausgänge; und
Anwenden einiger der Gewichtungen, die jedem der Ausgangs-Bins entsprechen, auf Ergebnisse der im Wesentlichen orthogonalisierenden Prozedur, um Symbole zu erhalten, die über jeden der Unterkanäle gesendet werden.
60. Verfahren nach Anspruch 52, bei dem das Empfangen das Empfangen von Informationen in Unterkanälen umfasst, die durch die Ausgangs-Bins und wenigstens zwei räumliche Richtungen, die jedem der Ausgangs-Bins zugeordnet sind, definiert sind, wobei die räumlichen Richtungen unabhängig für jedes der Ausgangs-Bins gewählt werden.
61. Verfahren nach Anspruch 60, bei dem die wenigstens zwei räumlichen Richtungen für jedes der Ausgangs-Bins zueinander orthogonal sind.
62. Verfahren nach Anspruch 60 oder 61, bei dem das Empfangen umfasst:
- Empfangen von Zeitbereichssymbolen über die Kanalausgänge;
Anwenden der den Zeitbereich im Wesentlichen orthogonalisierenden Prozedur unabhängig für jeden der Kanalausgänge auf die empfangenen Eingangszeitbereichssymbole; und
Anwenden der Gewichtungen auf Ergebnisse der den Zeitbereich im Wesentlichen orthogonalisierenden Prozedur, um Symbole zu erhalten, die über jeden der Unterkanäle gesendet werden.
63. Verfahren nach Anspruch 62, das ferner das Anwenden einer Decodierungsprozedur auf die über jeden der Unterkanäle gesendeten Symbole umfasst.
64. Verfahren nach Anspruch 63, bei dem die Decodierungsprozedur unabhängig für jedes der Ausgangs-Bins angewendet wird.
65. Verfahren nach Anspruch 63, bei dem die Decodierungsprozedur unabhängig für jede der räumlichen Richtungen angewendet wird.
66. Verfahren nach Anspruch 65, bei dem sämtliche räumlichen Richtungen zueinander orthogonal sind.
67. Verfahren nach Anspruch 63, bei dem die Decodierungsprozedur unabhängig für jeden der Unterkanäle angewendet wird.
68. Verfahren nach Anspruch 63, bei dem die Decodierungsprozedur basiert auf: einer Faltungscodierung, einer Reed-Solomon-Codierung, einer CRC-Codierung, einer Blockcodierung, einer Trellis-Codierung, einer Turbocodierung und einer Verschachtelung.
69. Verfahren nach Anspruch 60, bei dem die wenigstens zwei räumlichen Richtungen nicht für jedes der Ausgangs-Bins zueinander orthogonal sind.
70. Verfahren nach Anspruch 69, bei dem das Empfangen umfasst:
- Empfangen von Zeitbereichssymbolen über die Kanalausgänge;
für jeden der Kanalausgänge Anwenden der Gewichtungen auf die Zeitbereichssymbole, um Ergebnisse, die

jeder der räumlichen Richtungen entsprechen, zu erhalten;
Anwenden der den Zeitbereich im Wesentlichen orthogonalisierenden Prozedur auf die Ergebnisse unabhängig für jede der räumlichen Richtungen, um Symbole zu erhalten, die über jeden der Unterkanäle gesendet werden; und

Decodieren der Symbole, die über jeden der Unterkanäle gesendet werden, in Übereinstimmung mit einem Codierungsschema, das so optimiert ist, dass der Vorteil mehrerer räumlicher Richtungen genutzt wird.

71. Verfahren nach Anspruch 70, bei dem die Gewichtungen so gewählt werden, dass die Störung von nicht gewünschten Sendern minimiert wird.

72. Verfahren nach Anspruch 70, bei dem die Gewichtungen so gewählt werden, dass die durchschnittlich empfangene Leistung maximiert wird.

73. Verfahren nach Anspruch 70, bei dem das Codierungsschema eine mehrdimensionale Trellis-Codierungsprozedur umfasst.

74. Verfahren nach einem der Ansprüche 52 bis 73, bei dem die den Zeitbereich im Wesentlichen orthogonalisierende Prozedur zu einer Gruppe gehört, die aus einer schnellen Fourier-Transformation und aus einer inversen schnellen Fourier-Transformation besteht.

75. Verfahren nach einem der Ansprüche 52 bis 73, bei dem die den Zeitbereich im Wesentlichen orthogonalisierende Prozedur zu einer Gruppe gehört, die aus einer diskreten Kosinustransformation, einer Hilbert-Transformation, einer Wavelet-Transformation und einer Verarbeitung durch mehrere Frequenzumsetzer-/Bandpassfilter-Paare, die auf beabstandete Frequenzen zentriert sind, besteht.

76. Verfahren nach einem der Ansprüche 52 bis 75, bei dem der Kanal einen drahtlosen Kanal umfasst und bei dem die mehreren Kanalausgänge einer entsprechenden Mehrzahl von Empfängerantennenelementen zugeordnet sind.

77. Verfahren nach einem der Ansprüche 52 bis 76, das ferner umfasst:

Empfangen von wenigstens \square Frequenzbereich-Trainingssymbolen, die über einen bestimmten Eingang in den Kanal gesendet werden, über einen bestimmten der Kanalausgänge, wobei \square eine Erstreckung, gezählt in Symbolperioden, einer Dauer signifikanter Terme einer Impulsantwort einer Kanalkomponente ist, die den bestimmten Kanaleingang mit dem bestimmten Kanalausgang koppelt;

Anwenden der den Zeitbereich im Wesentlichen orthogonalisierenden Prozedur auf die wenigstens \square empfangenen Trainingssymbole, um eine Zeitbereichsantwort auf die Kanalkomponente zu erhalten; und
Anwenden einer Inversen der im Wesentlichen orthogonalisierenden Prozedur auf eine mit Nullen aufgefüllte Version der Zeitbereichsantwort, um eine Frequenzantwort für die Kanalkomponente zu erhalten.

78. Empfängersystem zum Empfangen von Informationen über mehrere Ausgänge von einem Kanal, wobei das Empfängersystem umfasst:

wenigstens ein Verarbeitungselement (200), das eine den Zeitbereich im Wesentlichen orthogonalisierende Prozedur anwendet, um den Kanal in Ausgangs-Bins zu unterteilen;
einen räumlichen Prozessor (210), der Gewichtungen unter den Kanalausgängen verwendet, um räumliche Richtungen zu definieren, wobei jedem Ausgangs-Bin wenigstens eine räumliche Richtung zugeordnet ist; und

wobei das Empfängersystem Informationen über Unterkanäle des Kanals empfängt, indem es wenigstens zwei unabhängige parallele Anwendungen der im Wesentlichen orthogonalisierenden Prozedur durch das wenigstens eine Verarbeitungselement verwendet, wobei jeder der Unterkanäle durch eine Kombination von Ausgangs-Bin und räumlicher Richtung definiert ist.

79. Empfängersystem nach Anspruch 78, bei dem die Gewichtungen so gewählt sind, dass die Störung von nicht gewünschten Sendern minimiert ist.

80. Empfängersystem nach Anspruch 78, bei dem die Gewichtungen auf der Grundlage der Charakterisierung eines gewünschten Signalunterraums gewählt sind.

81. Empfängersystem nach Anspruch 80, bei dem die Gewichtungen ferner auf der Grundlage der Charakterisierung eines nicht gewünschten Signalunterraums gewählt sind.

82. Empfängersystem nach Anspruch 81, bei dem die Charakterisierungen des gewünschten Signalunterraums und des nicht gewünschten Signalunterraums über die Zeit und/oder die Frequenz gemittelt sind.

83. Empfängersystem nach Anspruch 78, das ferner umfasst:

einen Systemeingang, der Eingangszeitbereichssymbole über die Kanalausgänge empfängt; und bei dem das wenigstens eine Verarbeitungselement die im Wesentlichen orthogonalisierende Prozedur auf die Zeitbereichseingangssymbole unabhängig für jeden der Kanalausgänge anwendet; und bei dem der räumliche Prozessor einige der Gewichtungen, die jedem der Ausgangs-Bins entsprechen, auf Ergebnisse der im Wesentlichen orthogonalisierenden Prozedur anwendet, um Symbole zu erhalten, die über jeden der Unterkanäle gesendet werden.

84. Empfängersystem nach Anspruch 78, wobei das Empfängersystem Informationen in Unterkanälen empfängt, die durch die Ausgangs-Bins und durch wenigstens zwei räumliche Richtungen, die jedem der Ausgangs-Bins zugeordnet sind, definiert sind, wobei jedes der Ausgangs-Bins gleiche zugeordnete räumliche Richtungen besitzt.

85. Empfängersystem nach Anspruch 84, das ferner umfasst:

einen Systemeingang, der Eingangszeitbereichssymbole über die Kanalausgänge empfängt; und bei dem der räumliche Prozessor für jeden der Kanalausgänge eine entsprechende der Gewichtungen auf die empfangenen Eingangszeitbereichssymbole anwendet, wobei jeder der Gewichtungen eine bestimmte der wenigstens zwei räumlichen Richtungen zugeordnet ist; und bei dem das wenigstens eine Verarbeitungselement für jede der wenigstens zwei räumlichen Richtungen die den Zeitbereich im Wesentlichen orthogonalisierende Prozedur unabhängig auf Ergebnisse der Anwendung der Gewichtungen anwendet, um Symbole zu erhalten, die über jeden der Unterkanäle gesendet werden.

86. Empfängersystem nach Anspruch 78, wobei das Empfängersystem Informationen in Unterkanälen empfängt, die durch die Ausgangs-Bins und wenigstens zwei räumliche Richtungen definiert sind, die jedem der Ausgangs-Bins zugeordnet sind, wobei die räumlichen Richtungen unabhängig für jedes der Ausgangs-Bins gewählt sind.

87. Empfängersystem nach Anspruch 86, bei dem die wenigstens zwei räumlichen Richtungen für jedes der Ausgangs-Bins zueinander orthogonal sind.

88. Empfängersystem nach Anspruch 86 oder 87, das ferner umfasst:

einen Systemeingang, der über die Kanalausgänge Zeitbereichssymbole empfängt; und bei dem das wenigstens eine Verarbeitungselement die den Zeitbereich im Wesentlichen orthogonalisierende Prozedur unabhängig für jeden der Kanalausgänge auf die empfangenen Eingangszeitbereichssymbole anwendet; und bei dem der räumliche Prozessor die Gewichtungen auf Ergebnisse der den Zeitbereich im Wesentlichen orthogonalisierenden Prozedur anwendet, um Symbole zu erhalten, die über jeden der Unterkanäle gesendet werden.

89. Empfängersystem nach Anspruch 88, bei dem die Gewichtungen in Übereinstimmungen mit Zerlegungen singulärer Werte von Matrizen, die die Kommunikation über jedes der Ausgangs-Bins des Kanals charakterisieren, ausgewählt werden.

90. Empfängersystem nach Anspruch 88 oder 89, das ferner ein Decodierungssystem umfasst, das auf die über jeden der Unterkanäle gesendeten Symbole eine Decodierungsprozedur anwendet.

91. Empfängersystem nach Anspruch 90, bei dem die Decodierungsprozedur unabhängig für jedes der Ausgangs-Bins angewendet wird.

92. Empfängersystem nach Anspruch 90, bei dem die Decodierungsprozedur unabhängig für jede der räumlichen Richtungen angewendet wird.

93. Empfängersystem nach Anspruch 92, bei dem die räumlichen Richtungen zueinander orthogonal sind.
94. Empfängersystem nach Anspruch 90, bei dem die Decodierungsprozedur für jeden der Unterkanäle unabhängig angewendet wird.
95. Empfängersystem nach Anspruch 90, bei dem die Decodierungsprozedur auf einer der folgenden Prozeduren basiert: einer Faltungscodierung, einer Reed-Solomon-Codierung, einer CRC-Codierung, einer Blockcodierung, einer Trellis-Codierung, einer Turbocodierung und einer Verschachtelung.
96. Empfängersystem nach Anspruch 86, bei dem die wenigstens zwei räumlichen Richtungen nicht für jedes der Ausgangs-Bins zueinander orthogonal sind.
97. Empfängersystem nach Anspruch 96, das ferner umfasst:
- einen Systemeingang, der die Zeitbereichssymbole über die Kanalausgänge empfängt; und bei dem der räumliche Prozessor für jeden der Kanalausgänge die Gewichtungen auf die Zeitbereichssymbole anwendet, um Ergebnissymbole zu erhalten, die jeder der räumlichen Richtungen entsprechen; und bei dem das wenigstens eine Verarbeitungselement die den Zeitbereich im Wesentlichen orthogonalisierende Prozedur unabhängig für jede der räumlichen Richtungen auf die Ergebnissymbole anwendet, um Symbole zu erhalten, die über jeden der Unterkanäle gesendet werden; und bei dem das Empfängersystem ferner umfasst:
- ein Decodierungssystem, das Symbole, die über jeden der Unterkanäle gesendet werden, in Übereinstimmung mit einem Codierungsschema decodiert, das so optimiert ist, dass der Vorteil mehrerer räumlicher Richtungen genutzt wird.
98. Empfängersystem nach Anspruch 97, bei dem die Gewichtungen so gewählt sind, dass die Störung von nicht gewünschten Sendern minimiert ist.
99. Empfängersystem nach Anspruch 97, bei dem die Gewichtungen so gewählt sind, dass die durchschnittlich empfangene Leistung maximiert ist.
100. Empfängersystem nach Anspruch 97, bei dem das Codierungsschema eine mehrdimensionale Trellis-Codierungsprozedur umfasst.
101. Empfängersystem nach einem der Ansprüche 78 bis 100, bei dem die den Zeitbereich im Wesentlichen orthogonalisierende Prozedur zu einer Gruppe gehört, die aus einer schnellen Fourier-Transformation und aus einer inversen schnellen Fourier-Transformation besteht
102. Empfängersystem nach einem der Ansprüche 78 bis 101, bei dem der Kanal einen drahtlosen Kanal umfasst und die mehreren Kanalausgänge einer entsprechenden Mehrzahl von Empfängerantennenelementen zugeordnet sind.
103. Sendersystem zum Senden von Informationen über mehrere Eingänge zu einem Kanal, wobei das Sendersystem umfasst:
- wenigstens ein Verarbeitungselement (190), das eine den Zeitbereich im Wesentlichen orthogonalisierende Prozedur ausführt, um den Kanal in Empfangs-Bins zu unterteilen;
- ein Codierungssystem (10), das auf Informationen ein Codierungsschema anwendet, das Informationen verteilt auf mehrere räumliche Richtungen verteilt; und
- wobei das Sendersystem Informationen, die durch das Codierungssystem codiert sind, in Unterkanälen des Kanals sendet, wobei jeder der Unterkanäle durch eine Kombination aus Eingangs-Bin und räumlicher Richtung definiert ist.
104. Sendersystem nach Anspruch 103, bei dem das Codierungsschema ein mehrdimensionales Trellis-Codierungsschema umfasst.
105. Sendersystem nach Anspruch 103 oder 104, bei dem die mehreren räumlichen Richtungen einem Senden über

einen einzigen Kanaleingang entsprechen.

106. Sendersystem nach Anspruch 103 oder 104, bei dem jede der mehreren räumlichen Richtungen einer Gewichtung unter den Kanaleingängen entspricht.

107. Sendersystem nach Anspruch 106, bei dem die Gewichtung auf ein Zeitbereichssignal angewendet wird.

108. Sendersystem nach einem der Ansprüche 103 bis 107, bei dem das Codierungsschema über Eingangs-Bins hinweg codiert.

109. Empfängersystem zum Empfangen von Informationen über mehrere Ausgänge von einem Kanal, wobei das Empfängersystem umfasst:

wenigstens ein Verarbeitungselement (200), das eine den Zeitbereich im Wesentlichen orthogonalisierende Prozedur ausführt, um den Kanal in Ausgangs-Bins zu unterteilen;
ein Decodierungssystem (150), das ein Codierungsschema aus empfangenen Informationen entfernt, wobei das Codierungsschema die Informationen vorteilhaft auf die mehreren räumlichen Richtungen verteilt; und

wobei das Empfängersystem die Informationen in Unterkanälen des Kanals empfängt, wobei jeder der Unterkanäle durch eine Kombination aus Ausgangs-Bin und räumlicher Richtung definiert ist.

110. Empfängersystem nach Anspruch 109, bei dem das Codierungsschema ein mehrdimensionales Trellis-Codierungsschema umfasst.

111. Empfängersystem nach Anspruch 109 oder 110, bei dem jede der mehreren räumlichen Richtungen einem Empfang über einen einzigen Kanalausgang entspricht.

112. Empfängersystem nach Anspruch 109 oder 110, bei dem jede der mehreren räumlichen Richtungen einer Gewichtung unter den Kanalausgängen entspricht.

113. Empfängersystem nach Anspruch 112, bei dem die Gewichtung auf ein Zeitbereichssignal angewendet wird.

114. Empfängersystem nach einem der Ansprüche 109 bis 113, bei dem das Codierungsschema über Ausgangs-Bins hinweg codiert.

Revendications

1. Procédé pour transmettre des informations via une pluralité d'entrées à un canal dans un système de communication numérique, le procédé comprenant les étapes consistant à :

fournir une procédure sensiblement d'orthogonalisation dans le domaine temporel pour diviser ledit canal en paquets d'entrée ;
fournir une ou plusieurs directions spatiales pour la communication définie par des pondérations correspondantes parmi lesdites entrées du canal dans lequel chaque paquet d'entrée comporte au moins une direction spatiale associée ; et
transmettre lesdites informations dans des sous-canaux en employant au moins deux applications parallèles indépendantes de ladite procédure sensiblement d'orthogonalisation dans le domaine temporel, les sous-canaux étant définis par une combinaison d'un paquet d'entrée et d'une direction spatiale.

2. Procédé selon la revendication 1, dans lequel lesdites pondérations définissent lesdites une ou plusieurs directions spatiales, de sorte que, chaque direction spatiale correspond à une communication via exactement une entrée de canal.

3. Procédé selon la revendication 1, dans lequel lesdites pondérations définissent ladite une ou plusieurs directions spatiales, de sorte que, chaque direction spatiale correspond à une communication via plus qu'une entrée de canal.

4. Procédé selon la revendication 1, dans lequel lesdites pondérations sont choisies pour minimiser l'interférence

avec des récepteurs non voulus.

5. Procédé selon la revendication 1, dans lequel lesdites pondérations sont choisies sur la base de la caractérisation d'un sous-espace de signal désiré.
6. Procédé selon la revendication 5, dans lequel lesdites pondérations sont choisies, en outre, sur la base de la caractérisation d'un sous-espace de signal non désiré.
7. Procédé selon la revendication 6, dans lequel lesdites caractérisations dudit sous-espace de signal désiré et dudit sous-espace de signal non désiré sont mises en moyenne sur, au moins un parmi un temps et une fréquence.
8. Procédé selon l'une quelconque des revendications précédentes, dans lequel la transmission comprend les étapes consistant à
 - fournir un groupe de symboles d'entrée dans lequel chaque symbole d'entrée correspond à un paquet d'entrée particulier de ladite procédure sensiblement d'orthogonalisation dans le domaine temporel ;
 - appliquer une desdites pondérations correspondant à chacun desdits paquets d'entrée à chacun desdits symboles d'entrée pour développer pour chacun desdits symboles d'entrée un vecteur de symboles spatialement traités, chaque élément dudit vecteur correspondant à une seule entrée de canal de ladite pluralité des entrées de canal ;
 - appliquer ladite procédure sensiblement d'orthogonalisation dans le domaine temporel indépendamment pour chacun desdites entrées de canal audit symbole spatialement traité ; et
 - transmettre les informations via lesdites entrées de canal en fonction des résultats de ladite procédure sensiblement d'orthogonalisation dans le domaine temporel.
9. Procédé selon l'une quelconque des revendications 1 à 7, dans lequel la transmission comprend la transmission des informations dans des sous-canaux définis par lesdits paquets d'entrée et au moins deux directions spatiales associées à chacun desdits paquets d'entrée, lesdites directions spatiales étant choisies indépendamment pour chacun desdits paquets d'entrée.
10. Procédé selon la revendication 9, dans lequel lesdites au moins deux directions spatiales sont mutuellement orthogonales pour chacun desdits paquets d'entrée.
11. Procédé selon la revendication 9 ou 10, dans lequel la transmission comprend :
 - fournir un groupe de symboles d'entrée dans lequel chaque symbole d'entrée correspond à un paquet d'entrée particulier de ladite procédure sensiblement d'orthogonalisation dans le domaine temporel et une direction particulière desdites au moins deux directions spatiales ;
 - pour chacune desdites directions spatiales appliquer une desdites pondérations pour définir les contributions à chacune desdites entrées de canal ;
 - pour chaque entrée de canal, appliquer indépendamment ladite procédure sensiblement d'orthogonalisation dans le domaine temporel au résultat de l'application desdites pondérations, et
 - transmettre les informations via lesdites entrées de canal en fonction du résultat de l'application de ladite procédure sensiblement d'orthogonalisation dans le domaine temporel.
12. Procédé selon la revendication 11, comprenant, en outre, l'application d'une procédure de codage pour développer ledit groupe des symboles d'entrée.
13. Procédé selon la revendication 12, dans lequel ladite procédure de codage est appliquée indépendamment pour chacun desdits paquets d'entrée.
14. Procédé selon la revendication 12, dans lequel ladite procédure de codage est appliquée indépendamment pour chacune desdites directions spatiales.
15. Procédé selon la revendication 14, dans lequel toutes lesdites directions spatiales sont mutuellement orthogonales.
16. Procédé selon la revendication 12, dans lequel ladite procédure de codage est appliquée indépendamment pour chacun desdits sous-canaux.

17. Procédé selon l'une quelconque des revendications 12 à 16, dans lequel ladite procédure de codage appartient à un groupe qui est constitué de : codage convolutionnel, codage Reed-Solomon, codage CRC, codage en bloc, codage en treillis, turbo codage et entrelacement.
- 5 18. Procédé selon la revendication 9, dans lequel lesdites au moins deux directions spatiales ne sont pas orthogonales pour chacun desdits paquets d'entrée.
19. Procédé selon la revendication 18, dans lequel la transmission comprend les étapes consistant à :
 - 10 coder lesdites informations pour développer des symboles correspondant à chacun desdits sous-canaux, ledit codage étant optimisé pour prendre avantage des multiples directions spatiales ;
appliquer ladite procédure sensiblement d'orthogonalisation dans le domaine temporel indépendamment aux symboles correspondant à chacune desdites au moins deux directions spatiales ;
appliquer lesdites pondérations aux résultats desdites applications indépendantes de ladite procédure sensiblement d'orthogonalisation dans le domaine temporel ; et
15 transmettre via lesdites entrées de canaux en fonction des résultats de l'application desdites pondérations.
20. Procédé selon la revendication 19, dans lequel lesdites pondérations sont choisies pour minimiser l'interférence avec des récepteurs non voulus.
- 20 21. Procédé selon la revendication 19, dans lequel lesdites pondérations sont choisies pour maximiser la puissance moyenne reçue.
22. Procédé selon la revendication 19, dans lequel le codage comprend l'application d'une procédure de codage en treillis multi-dimensionnelle.
- 25 23. Procédé selon l'une quelconque des revendications précédentes, dans lequel ladite procédure sensiblement d'orthogonalisation dans le domaine temporel appartient à un groupe qui est constitué d'une transformée de Fourier rapide inverse et une transformée de Fourier rapide.
- 30 24. Procédé selon l'une quelconque des revendications précédentes, dans lequel ledit canal comprend un canal sans fil et ladite pluralité des entrées de canal est associée à une pluralité correspondante d'éléments d'antenne d'émetteur.
- 35 25. Procédé selon l'une quelconque des revendications précédentes, comprenant, en outre : l'attribution de chargement de bits et de puissance parmi ladite pluralité des sous-canaux.
26. Système émetteur pour transmettre des informations via une pluralité d'entrées à un canal, ledit système d'émetteur comprenant :
 - 40 au moins un élément de traitement (190) qui applique une procédure sensiblement d'orthogonalisation dans le domaine temporel pour diviser ledit canal en paquets d'entrée ;
un processeur spatial (230) employant des pondérations parmi les entrées de canal pour définir des directions spatiales dans lequel chaque paquet d'entrée a au moins une direction spatiale associée ; et
45 dans lequel ledit système d'émetteur transmet des informations dans des sous-canaux dudit canal, chacun desdits sous-canaux étant définis par une combinaison d'un paquet d'entrée et d'une direction spatiale, en employant ledit au moins un élément de traitement pour au moins deux applications indépendantes de ladite procédure sensiblement d'orthogonalisation dans le domaine temporel.
- 50 27. Système émetteur selon la revendication 26, dans lequel lesdites pondérations définissent ladite une ou plusieurs directions spatiales, de sorte que chaque direction spatiale correspond à la communication via plus qu'une entrée de canal.
28. Système émetteur selon la revendication 26, dans lequel lesdites pondérations sont choisies pour minimiser l'interférence avec des récepteurs non voulus.
- 55 29. Système émetteur selon la revendication 26, dans lequel lesdites pondérations sont choisies sur la base de la caractérisation d'un sous-espace de signal désiré.

30. Emetteur selon la revendication 29, dans lequel lesdites pondérations sont choisies, en outre, sur la base de la caractérisation d'un sous-espace de signal non désiré.
- 5 31. Système émetteur selon la revendication 30, dans lequel lesdites caractérisations dudit sous-espace de signal désiré et dudit sous-espace de signal non désiré sont mises en moyenne sur au moins un parmi le temps et la fréquence.
32. Système émetteur selon la revendication 26, comprenant, en outre :
- 10 une entrée de système qui reçoit un groupe de symboles d'entrée dans lequel chaque symbole d'entrée correspond à un paquet d'entrée particulier de ladite procédure sensiblement d'orthogonalisation dans le domaine temporel ; et dans lequel
- ledit processeur spatial applique une desdites pondérations correspondant à chacun desdits paquets d'entrée, à chacun desdits symboles d'entrée pour développer pour chacun desdits symboles d'entrée un vecteur de
- 15 symboles spatialement traité, chaque élément dudit vecteur correspondant à une seule entrée de canal de ladite pluralité des entrées de canal ; et dans lequel
- ledit au moins un élément de traitement applique ladite procédure sensiblement d'orthogonalisation dans le domaine temporel indépendamment pour chacune desdites entrées de canal audit symbole spatialement traité ; et dans lequel
- 20 ledit système d'émetteur transmet via lesdites entrées de canal en fonction des résultats de ladite procédure sensiblement d'orthogonalisation dans le domaine temporel.
33. Système émetteur selon la revendication 26, dans lequel les informations sont transmises dans des sous-canaux et définis par lesdits paquets d'entrée et au moins deux directions spatiales associées à chacun desdits paquets d'entrée, lesdites directions spatiales étant choisies indépendamment pour chacun desdits paquets d'entrée.
- 25 34. Système émetteur selon la revendication 33, dans lequel au moins deux directions spatiales sont mutuellement orthogonales pour chacun desdits paquets d'entrée.
- 30 35. Système émetteur selon la revendication 33 ou 34, comprenant, en outre :
- une entrée de système qui reçoit un groupe de symboles d'entrée dans lequel chaque symbole d'entrée correspond à un paquet d'entrée particulier de ladite procédure sensiblement d'orthogonalisation dans le domaine temporel et une direction particulière desdites au moins deux directions spatiales ; et dans lequel
- 35 ledit processeur spatial, pour chacune desdites directions spatiales, applique une desdites pondérations pour définir les contributions à chacune desdites entrées de canal ; et dans lequel
- ledit au moins un élément de traitement applique indépendamment ladite procédure sensiblement d'orthogonalisation dans le domaine temporel aux résultats de l'application desdites pondérations ; et dans lequel
- 40 ledit système d'émetteur transmet via lesdites entrées de canal en fonction des résultats de l'application de ladite procédure sensiblement d'orthogonalisation dans le domaine temporel.
36. Système émetteur selon la revendication 35, dans lequel lesdites pondérations sont sélectionnées en conformité avec des décompositions de valeurs singulières de matrice caractérisant la communication via chaque paquet d'entrée dudit canal.
- 45 37. Système émetteur selon la revendication 35 ou 36, comprenant, en outre, un système de codage qui applique une procédure de codage pour développer ledit groupe des symboles d'entrée.
38. Système émetteur selon la revendication 37, dans lequel ladite procédure de codage est appliquée indépendamment pour chacun desdits paquets d'entrée.
- 50 39. Système émetteur selon la revendication 37, dans lequel ladite procédure de codage est appliquée indépendamment pour chacune desdites directions spatiales.
- 55 40. Système émetteur selon la revendication 39, dans lequel chacune desdites directions spatiales sont mutuellement orthogonales.
41. Système émetteur selon la revendication 37, dans lequel ladite procédure de codage est appliquée indépendamment

ment pour chacun desdits sous-canaux.

- 5 42. Système émetteur selon l'une quelconque des revendications 37 à 41, dans lequel ladite procédure de codage appartient à un groupe qui est constitué de : codage convolutionnel, codage Reed-Solomon, codage CRC, codage en bloc, codage en treillis, turbo codage et entrelacement.
43. Système émetteur selon la revendication 33, dans lequel lesdites au moins deux directions spatiales ne sont pas mutuellement orthogonales pour chacun desdits paquets d'entrée.
- 10 44. Système émetteur selon la revendication 43 comprenant, en outre :
- un système de codage qui code lesdites informations pour développer des symboles correspondant à chacun desdits sous-canaux, ledit codage étant optimisé pour prendre avantage des multiples directions spatiales ; et dans lequel
- 15 ledit au moins un élément de traitement applique ladite procédure sensiblement d'orthogonalisation dans le domaine temporel indépendamment aux symboles correspondant à chacune desdites au moins deux directions spatiales ; et dans lequel
- ledit processeur spatial applique lesdites pondérations aux résultats desdites applications indépendantes de ladite procédure sensiblement d'orthogonalisation dans le domaine temporel ; et dans lequel
- 20 ledit système d'émetteur transmet via ladite pluralité des entrées de canal sensibles aux résultats de l'application desdites pondérations.
45. Système émetteur selon la revendication 44, dans lequel lesdites pondérations sont sélectionnées, de sorte qu'il n'existe une association univoque entre les entrées de canal et les directions spatiales.
- 25 46. Système émetteur selon la revendication 44, dans lequel lesdites pondérations sont choisies pour minimiser l'interférence avec les récepteurs non voulus.
47. Système émetteur selon la revendication 44, dans lequel lesdites pondérations sont choisies pour maximiser la puissance moyenne reçue.
- 30 48. Système émetteur selon la revendication 44, dans lequel ledit système de codage applique une procédure de codage en treillis multi-dimensionnelle.
- 35 49. Système émetteur selon l'une quelconque des revendications 26 à 48, dans lequel ladite procédure sensiblement d'orthogonalisation dans le domaine temporel appartient à un groupe qui est constitué d'une transformée de Fourier rapide inverse et d'une transformée de Fourier rapide.
- 40 50. Système émetteur selon l'une quelconque des revendications 26 à 49, dans lequel ledit canal comprend un canal sans fil et ladite pluralité des entrées de canal est associée à une pluralité correspondante d'éléments d'antenne d'émetteur.
51. Système émetteur selon l'une quelconque des revendications 26 à 50, comprenant, en outre :
- 45 un système de chargement de bits qui attribue le chargement de bits et la puissance parmi ladite pluralité des sous-canaux.
52. Procédé pour recevoir des informations via une pluralité de sorties d'un canal dans un système de communication numérique, ledit procédé comprenant les étapes consistant à :
- 50 fournir une procédure sensiblement d'orthogonalisation dans le domaine temporel pour diviser ledit canal en paquets de sortie ;
- fournir une ou plusieurs directions spatiales pour communication définie par des pondérations correspondantes parmi lesdites sorties de canal dans lequel chaque paquet de sortie a au moins une direction spatiale associée ; et
- 55 recevoir les informations via les sous-canaux dudit canal en employant au moins deux applications parallèles indépendantes de ladite procédure sensiblement d'orthogonalisation dans le domaine temporel, chaque sous-canal étant défini par une combinaison d'un paquet de sortie et d'une direction spatiale.

53. Procédé selon la revendication 52, dans lequel lesdites pondérations définissent ladite une ou plusieurs directions spatiales, de sorte que, chaque direction spatiale correspond à la communication via exactement une sortie de canal.
- 5 54. Procédé selon la revendication 52, dans lequel lesdites pondérations définissent ladite une ou plusieurs directions spatiales, de sorte que, chaque direction spatiale correspond à la communication via plus qu'une sortie de canal.
55. Procédé selon la revendication 52, dans lequel lesdites pondérations sont choisies pour minimiser l'interférence à partir d'émetteurs non désirés.
- 10 56. Procédé selon la revendication 52, dans lequel lesdites pondérations sont choisies sur la base de la caractérisation d'un sous-espace de signal désiré.
57. Procédé selon la revendication 56, dans lequel lesdites pondérations sont choisies, en outre, sur la base de la caractérisation d'un sous-espace de signal non désiré.
- 15 58. Procédé selon la revendication 57, dans lequel lesdites caractérisations du sous-espace de signal désiré et du sous-espace de signal non désiré sont mises en moyenne sur au moins un parmi le temps et la fréquence .
- 20 59. Procédé selon l'une quelconque des revendications 52 à 58, dans lequel la réception comprend :
- recevoir des symboles d'entrée dans le domaine temporel via lesdites sorties de canal
appliquer ladite procédure sensiblement d'orthogonalisation auxdits symboles d'entrée dans le domaine temporel indépendamment pour chacune desdites sorties de canal ; et
25 appliquer une parmi lesdites pondérations correspondant à chacun desdits paquets de sortie aux résultats de ladite procédure sensiblement d'orthogonalisation pour obtenir les symboles transmis via chacun desdits sous-canaux.
60. Procédé selon la revendication 52, dans lequel la réception comprend la réception d'information dans des sous-canaux définis par lesdits paquets de sortie et au moins deux directions spatiales associées à chacun desdits paquets de sortie, lesdites directions spatiales étant choisies indépendamment pour chacun desdits paquets de sortie.
- 30 61. Procédé selon la revendication 60, dans lequel lesdites au moins deux directions spatiales sont mutuellement orthogonales pour chacun desdits paquets de sortie.
- 35 62. Procédé selon la revendication 60 ou 61, dans lequel la réception comprend :
- recevoir des symboles dans le domaine temporel via lesdites sorties de canal ;
40 pour chacune desdites sortie de canal, appliquer indépendamment ladite procédure sensiblement d'orthogonalisation dans le domaine temporel auxdits symboles d'entrée reçus dans le domaine temporel ; et
appliquer lesdites pondérations aux résultats de ladite procédure sensiblement d'orthogonalisation dans le domaine temporel pour obtenir les symboles transmis via chacun desdits sous-canaux.
- 45 63. Procédé selon la revendication 62, comprenant, en outre, l'application d'une procédure de décodage auxdits symboles transmis via chacun desdits sous-canaux.
64. Procédé selon la revendication 63, de ladite procédure de décodage est appliquée indépendamment pour chacun desdits paquets de sortie.
- 50 65. Procédé selon la revendication 63, dans lequel ladite procédure de décodage est appliquée indépendamment pour chacune desdites directions spatiales.
66. Procédé selon la revendication 65, dans lequel chacune desdites directions spatiales sont mutuellement orthogonales.
- 55 67. Procédé selon la revendication 63, dans lequel ladite procédure de décodage est appliquée indépendamment pour chacun desdits sous-canaux.

68. Procédé selon la revendication 63, dans lequel ladite procédure de décodage est basée sur une procédure parmi : codage convolutionnel, codage Reed-Solomon, codage CRC, codage en bloc, codage en treillis, turbo codage et entrelacement.

5 69. Procédé selon la revendication 60, dans lequel lesdites au moins deux directions spatiales ne sont pas mutuellement orthogonales pour chacun desdits paquets de sortie.

70. Procédé selon la revendication 69, dans lequel la réception comprend :

10 recevoir des symboles dans le domaine temporel via lesdites sorties de canal ;
pour chacune desdites sorties de canal, appliquer lesdites pondérations auxdits symboles dans le domaine temporel pour obtenir les résultats correspondant à chacune desdites directions spatiales ;
appliquer ladite procédure sensiblement d'orthogonalisation dans le domaine temporel auxdits résultats indépendamment pour chacune desdites directions spatiales pour obtenir les symboles transmis via chacun desdits sous-canaux ; et
15 décoder lesdits symboles transmis via chacun desdits sous-canaux en conformité avec un schéma de codage optimisé pour prendre avantage des multiples directions spatiales.

20 71. Procédé selon la revendication 70, dans lequel lesdites pondérations sont choisies pour minimiser l'interférence à partir d'émetteurs non voulus.

72. Procédé selon la revendication 70, dans lequel lesdites pondérations sont choisies pour maximiser la puissance moyenne reçue.

25 73. Procédé selon la revendication 70, dans lequel ledit schéma de codage comprend une procédure de codage en treillis multi-dimensionnelle.

30 74. Procédé selon l'une quelconque des revendications 52 à 73, dans lequel ladite procédure sensiblement d'orthogonalisation dans le domaine temporel appartient à un groupe qui est constitué d'une transformée de Fourier rapide et d'une transformée de Fourier rapide inverse.

35 75. Procédé selon l'une quelconque des revendications 52 à 73, dans lequel ladite procédure sensiblement d'orthogonalisation dans le domaine temporel appartient à un groupe qui est constitué de transformée cosinus discret, transformée Hilbert, transformée en onde-lettes et traitement par l'intermédiaire d'une pluralité de paires de convertisseur de fréquence/paires de filtre passe bande centrées sur des fréquences espacées.

40 76. Procédé selon l'une quelconque des revendications 52 à 75, dans lequel ledit canal comprend un canal sans fil et ladite pluralité des sorties du canal est associée à une pluralité correspondante d'éléments d'antenne de récepteur.

77. Procédé selon l'une quelconque des revendications 52 à 76 comprenant, en outre :

45 recevoir via une sortie particulière desdites sorties de canal, au moins u symbole d'apprentissage dans le domaine de la fréquence transmis via une entrée particulière audit canal, u étant une étendue en périodes de symboles d'une durée des termes significatives d'une réponse impulsionnelle d'une composante du canal couplant ladite entrée particulière de canal et ladite sortie particulière de canal;
appliquer ladite procédure sensiblement d'orthogonalisation dans le domaine temporel audit au moins u symboles d'apprentissage reçus pour obtenir une réponse dans le domaine temporel pour ladite composante de canal ; et
50 appliquer un inverse de ladite procédure sensiblement d'orthogonalisation à une version remplie de zéro de ladite réponse dans le domaine temporel pour obtenir une réponse en fréquence pour ladite composante du canal.

55 78. Système récepteur pour recevoir des informations via une pluralité de sorties provenant d'un canal, ledit système de récepteur comprenant :

au moins un élément de traitement (200) qui applique une procédure sensiblement d'orthogonalisation dans le domaine temporel pour diviser ledit canal en paquets de sortie ;

un processeur spatial (210) employant les pondérations parmi lesdites sorties de canal pour définir les directions spatiales dans lequel chaque paquet de sortie comporte au moins une direction spatiale associée ; et dans lequel ledit système de récepteur reçoit des informations via les sous-canaux dudit canal, en employant au moins deux applications parallèles indépendantes de ladite procédure sensiblement d'orthogonalisation par ledit au moins un élément de traitement, chacun desdits sous-canaux étant défini par une combinaison d'un paquet de sortie et d'une direction spatiale.

79. Système récepteur selon la revendication 78, dans lequel lesdites pondérations sont choisies pour minimiser l'interférence à partir d'émetteurs non désirés.

80. Système récepteur selon la revendication 78, dans lequel lesdites pondérations sont choisies sur la base de la caractérisation d'un sous-espace de signal désiré.

81. Système récepteur selon la revendication 80, dans lequel lesdites pondérations sont choisies, en outre, sur la base de la caractérisation d'un sous-espace de signal non désiré.

82. Système récepteur selon la revendication 81, dans lequel lesdites caractérisations dudit sous-espace de signal désiré et dudit sous-espace de signal non désiré sont mises en moyenne sur au moins un parmi le temps et la fréquence.

83. Système récepteur selon la revendication 78, comprenant, en outre :

une entrée de système qui reçoit les symboles d'entrée dans le domaine temporel via lesdites sorties du canal ; et dans lequel

ledit au moins un élément de traitement applique ladite procédure sensiblement d'orthogonalisation audit symbole d'entrée dans le domaine temporel indépendamment pour chacune desdites sorties de canal ; et dans lequel

ledit processeur spatial applique des pondérations parmi lesdites pondérations correspondant à chacun desdits paquets de sortie aux résultats de ladite procédure sensiblement d'orthogonalisation pour obtenir les symboles transmis via chacun desdits sous-canaux.

84. Système récepteur selon la revendication 78, dans lequel ledit système récepteur reçoit les informations dans les sous-canaux définis par lesdits paquets de sortie et au moins deux directions spatiales associées à chacun desdits paquets de sortie, chacun desdits paquets de sortie ayant des directions spatiales associées identiques.

85. Système récepteur selon la revendication 84, comprenant, en outre :

une entrée de système qui reçoit les symboles d'entrée dans le domaine temporel via lesdites sorties de canal ; et dans lequel

ledit processeur spatial pour chacune desdites sorties de canal applique une pondération correspondante parmi lesdites pondérations audit symbole d'entrée reçu dans le domaine temporel, chacune desdites pondérations étant associée à une direction particulière parmi lesdites au moins deux directions spatiales ; et dans lequel

ledit au moins un élément de traitement pour chacune desdites au moins deux directions spatiales, applique indépendamment ladite procédure sensiblement d'orthogonalisation dans le domaine temporel aux résultats de l'application desdites pondérations pour obtenir les symboles transmis via chacun desdits sous-canaux.

86. Système récepteur selon la revendication 78, dans lequel ledit système récepteur reçoit les informations dans les sous-canaux définis par lesdits paquets de sortie et au moins les deux directions spatiales associées à chacun desdits paquets de sortie, lesdites directions spatiales étant choisies indépendamment pour chacun desdits paquets de sortie.

87. Système récepteur selon la revendication 86, dans lequel lesdites au moins deux directions spatiales sont mutuellement orthogonales pour chacun desdits paquets de sortie.

88. Système récepteur selon la revendication 86 ou 87, comprenant, en outre :

une entrée de système qui reçoit les symboles dans le domaine temporel via lesdites sorties de canal ; et

dans lequel

ledit au moins un élément de traitement pour chacune desdites sorties de canal, applique indépendamment ladite procédure sensiblement d'orthogonalisation dans le domaine temporel audit symbole d'entrée reçu dans le domaine temporel ; et dans lequel

ledit processeur spatial applique lesdites pondérations aux résultats de ladite procédure sensiblement d'orthogonalisation dans le domaine temporel pour obtenir les symboles transmis via chacun desdits sous-canaux.

89. Système récepteur selon la revendication 88, dans lequel lesdites pondérations sont sélectionnées en conformité avec des décompositions en valeurs singulières des matrices caractérisant la communication via chaque paquet de sortie dudit canal.

90. Système récepteur selon la revendication 88 ou 89, comprenant, en outre, un système de décodage qui applique une procédure de décodage auxdits symboles transmis via chacun desdits sous-canaux.

91. Système récepteur selon la revendication 90, dans lequel ladite procédure de décodage est appliquée indépendamment pour chacun desdits paquets de sortie.

92. Système récepteur selon la revendication 90, dans lequel ladite procédure de décodage est appliquée indépendamment pour chacune desdites directions spatiales.

93. Système récepteur selon la revendication 92, dans lequel chacune desdites directions spatiales sont mutuellement orthogonales.

94. Système récepteur selon la revendication 90, dans lequel ladite procédure de décodage est appliquée indépendamment pour chacun desdits sous-canaux.

95. Système récepteur selon la revendication 90, dans lequel ladite procédure de décodage est basée sur une procédure parmi : codage convolutionnel, codage Reed-Solomon, codage CRC, codage en bloc, codage en treillis, turbo codage et entrelacement.

96. Système récepteur selon la revendication 86, dans lequel lesdites au moins deux directions spatiales ne sont pas mutuellement orthogonales pour chacun desdits paquets de sortie.

97. Système récepteur selon la revendication 96, comprenant, en outre :

une entrée de système qui reçoit des symboles dans le domaine temporel via lesdites sorties de canal ; et dans lequel

ledit processeur spatial pour chacune desdites sorties de canal, applique lesdites pondérations auxdits symboles dans le domaine temporel pour obtenir des symboles résultants correspondant à chacune desdites directions spatiales ; et dans lequel

ledit au moins un élément de traitement applique ladite procédure sensiblement d'orthogonalisation dans le domaine temporel auxdits symboles résultants indépendamment pour chacune desdites directions spatiales pour obtenir les symboles transmis via chacun desdits sous-canaux et dans lequel ledit système récepteur comprend, en outre :

un système de décodage qui décode les symboles transmis via chacun desdits sous-canaux en conformité avec un schéma de codage optimisé pour prendre avantage des multiples directions spatiales.

98. Système récepteur selon la revendication 97, dans lequel lesdites pondérations sont choisies pour minimiser l'interférence à partir d'émetteurs non désirés.

99. Système récepteur selon la revendication 97, dans lequel lesdites pondérations sont choisies pour maximiser la puissance moyenne reçue.

100. Système récepteur selon la revendication 97, dans lequel ledit schéma de codage comprend une procédure de codage en treillis multi-dimensionnelle.

101. Système récepteur selon l'une quelconque des revendications 78 à 100, dans lequel ladite procédure sensiblement

d'orthogonalisation dans le domaine temporel appartient à un groupe qui est constitué d'une transformée de Fourier rapide et d'une transformée de Fourier rapide inverse.

5 102.Système récepteur selon l'une quelconque des revendications 78 à 101, dans lequel ledit canal comprend un canal sans fil et ladite pluralité des sorties de canal est associée à une pluralité correspondante d'éléments d'antenne de récepteur.

10 103.Système émetteur pour transmettre de l'information via une pluralité d'entrées à un canal, ledit système émetteur comprenant :

au moins un élément de traitement (190) qui exécute une procédure sensiblement d'orthogonalisation dans le domaine temporel pour diviser ledit canal en paquets d'entrée ; un système de codage (10) qui applique un schéma de codage aux informations, ledit schéma de codage distribue de manière avantageuse l'information parmi de multiples directions spatiales ; et
15 dans lequel ledit système d'émetteur transmet l'information telle que codée par le système de codage dans des sous-canaux dudit canal, chacun desdits sous-canaux étant défini par une combinaison d'un paquet d'entrée et d'une direction spatiale.

20 104.Système émetteur selon la revendication 103, dans lequel ledit schéma de codage comprend un schéma de codage en treillis multi-dimensionnel.

105.Système d'émetteur selon la revendication 103 ou 104, dans lequel, chacune desdites multiples directions spatiales correspond à la transmission via une seule entrée de canal.

25 106.Système d'émetteur selon la revendication 103 ou 104, dans lequel, chacune desdites multiples directions spatiales correspond à une pondération parmi lesdites entrées de canal.

30 107.Système d'émetteur selon la revendication 106, dans lequel ladite pondération est appliquée à un signal dans le domaine temporel.

108.Système d'émetteur selon l'une quelconque des revendications 103 à 107, dans lequel ledit schéma de codage code à travers les paquets d'entrée.

35 109.Système récepteur pour recevoir de l'information via une pluralité de sorties provenant d'un canal, le système récepteur comprenant :

au moins un élément de traitement (200) qui exécute une procédure sensiblement d'orthogonalisation dans le domaine temporel pour diviser ledit canal en paquets sortie ;
un système de décodage (150) qui supprime un schéma de codage à partir de l'information reçue, ledit schéma de codage distribuant de manière avantageuse l'information parmi de multiples directions spatiales ; et
40 dans lequel ledit système de récepteur reçoit ladite information dans les sous-canaux dudit canal, chacun desdits sous-canaux étant défini par une combinaison d'un paquet de sortie et d'une direction spatiale.

45 110.Système récepteur selon la revendication 109, dans lequel ledit schéma de codage comprend un schéma de codage en treillis multi-dimensionnel.

111.Système récepteur selon la revendication 109 ou 110, dans lequel chacune desdites multiples directions spatiales correspond à la réception via une seule sortie de canal.

50 112.Système récepteur selon la revendication 109 ou 110, dans lequel chacune desdites multiples directions spatiales correspond à une pondération parmi lesdites sorties de canal.

55 113.Système récepteur selon la revendication 112, dans lequel ladite pondération est appliquée à un signal dans le domaine temporel.

114.Système récepteur selon l'une quelconque des revendications 109 à 113, dans lequel ledit schéma de codage code à travers les paquets de sortie.




FIG. 1




FIG. 2




FIG. 3




FIG. 4

Multipath can be one or more paths with polarization A and one or more paths with polarization B. The two sets of paths may or may not be orthogonal.




FIG. 5

Multipath can be more paths between a remote and one radio port and one or more paths between the remote and another radio port.




FIG. 6




FIG. 7




FIG. 8




FIG. 9




FIG. 10




FIG. 11




FIG. 12




FIG. 13




FIG. 14




FIG. 15




FIG. 16




FIG. 17




FIG. 18




FIG. 19




FIG. 20




FIG. 21




FIG. 22




FIG. 23




FIG. 24




FIG. 25




FIG. 26